



# **XC8155, XC8160**

---

## **User's Guide**

**February 2018**

**[www.lexmark.com](http://www.lexmark.com)**

---

Machine type(s):

7564

Model(s):

596, 598

# Contents

- Safety information.....7**
  - Conventions.....7
- Learning about the printer..... 10**
  - Finding information about the printer..... 10
  - Selecting a location for the printer..... 11
  - Printer configurations..... 12
  - Attaching cables..... 14
  - Using the control panel..... 16
  - Understanding the status of the power button and indicator light..... 17
  - Using the home screen.....17
  - Menu map.....18
  - Printing a menu settings page.....20
- Setting up and using the home screen applications.....21**
  - Customizing the home screen..... 21
  - Setting up Forms and Favorites..... 21
  - Setting up Card Copy.....21
  - Using Shortcut Center.....22
  - Setting up Scan Center.....22
  - Using Customer Support.....22
  - Setting up Device Quotas.....22
  - Using QR Code Generator.....23
  - Using Google Drive.....23
  - Using Display Customization.....24
  - Configuring Eco-Settings..... 24
  - Managing contacts.....24
    - Adding contacts..... 24
    - Adding groups..... 25
    - Editing contacts or groups ..... 25
    - Deleting contacts or groups ..... 25
- Setting up and using the accessibility features.....27**
  - Enabling Magnification mode.....27
  - Activating Voice Guidance.....27

Adjusting the Voice Guidance speech rate.....	27
Enabling spoken passwords or personal identification numbers.....	27
Navigating the screen using gestures.....	28
Using the keyboard on the display.....	28

## **Loading paper and specialty media..... 29**

Setting the size and type of the specialty media.....	29
Configuring Universal paper settings.....	29
Loading trays.....	29
Loading the multipurpose feeder.....	31
Linking trays.....	32

## **Printing..... 33**

Printing from a computer.....	33
Printing forms.....	33
Printing from a mobile device.....	33
Printing from a flash drive.....	34
Supported flash drives and file types.....	35
Configuring confidential jobs.....	36
Printing held jobs.....	36
Printing a font sample list.....	37
Printing a directory list.....	37
Canceling a print job.....	37

## **Copying..... 38**

Making copies.....	38
Copying photos.....	38
Copying on letterhead.....	38
Copying on both sides of the paper.....	38
Reducing or enlarging copies.....	39
Collating copies.....	39
Placing separator sheets between copies.....	39
Copying multiple pages onto a single sheet.....	39
Creating a copy shortcut.....	39

## **E-mailing..... 40**

Setting up the e-mail function.....	40
-------------------------------------	----

Configuring e-mail settings.....	40
Sending an e-mail.....	40
Creating an e-mail shortcut.....	41

## **Faxing.....42**

Setting up the printer to fax.....	42
Sending a fax.....	55
Scheduling a fax.....	56
Creating a fax destination shortcut.....	56
Changing the fax resolution.....	56
Adjusting the fax darkness.....	56
Viewing a fax log.....	57
Blocking junk faxes.....	57
Holding faxes.....	57
Forwarding a fax.....	57

## **Scanning.....58**

Scanning to an FTP server.....	58
Creating an FTP shortcut.....	58
Scanning to a flash drive.....	58
Sending scanned documents to a computer.....	59

## **Securing the printer.....60**

Locating the security slot.....	60
Erasing printer memory.....	60
Erasing printer hard disk memory.....	60
Configuring printer hard disk encryption.....	61
Restoring factory default settings.....	61
Statement of Volatility.....	61

## **Maintaining the printer.....63**

Adjusting the speaker volume.....	63
Networking.....	64
Setting up serial printing (Windows only).....	65
Cleaning printer parts.....	65
Ordering parts and supplies.....	68
Replacing parts and supplies.....	71



Storing supplies.....	107
Moving the printer.....	108
Saving energy and paper.....	108
Recycling.....	109

## **Clearing jams..... 111**

Avoiding jams.....	111
Identifying jam locations.....	112
Paper jam in trays.....	114
Paper jam in the multipurpose feeder.....	115
Paper jam in the automatic document feeder.....	116
Paper jam in the standard bin.....	118
Paper jam in door B.....	119
Paper jam in the finisher bin.....	122
Staple jam in door G.....	124
Paper jam in door K.....	127
Paper jam in door J.....	129
Paper jam in door N.....	130
Paper jam in door L.....	131
Paper jam in the staple finisher bin.....	132
Staple jam in door J.....	133

## **Troubleshooting..... 136**

Network connection problems.....	136
Hardware options problems.....	138
Issues with supplies.....	140
Paper feed problems.....	142
Printing problems.....	146
Color quality problems.....	168
Faxing problems.....	171
Scanning problems.....	174
Contacting customer support.....	177

## **Upgrading and migrating..... 178**

Hardware.....	178
Software.....	200
Firmware.....	201

---

<b>Notices.....</b>	<b>202</b>
<b>Index.....</b>	<b>206</b>

# Safety information

## Conventions

**Note:** A *note* identifies information that could help you.

**Warning:** A *warning* identifies something that could damage the product hardware or software.

**CAUTION:** A *caution* indicates a potentially hazardous situation that could injure you.

Different types of caution statements include:



**CAUTION—POTENTIAL INJURY:** Indicates a risk of injury.



**CAUTION—SHOCK HAZARD:** Indicates a risk of electrical shock.



**CAUTION—HOT SURFACE:** Indicates a risk of burn if touched.



**CAUTION—TIPPING HAZARD:** Indicates a crush hazard.



**CAUTION—PINCH HAZARD:** Indicates a risk of being caught between moving parts.



**CAUTION—ROTATING FAN BLADES:** Indicates a risk of laceration from moving fan blades.



**CAUTION—POTENTIAL INJURY:** To avoid the risk of fire or electrical shock, connect the power cord to an appropriately rated and properly grounded electrical outlet that is near the product and easily accessible.



**CAUTION—POTENTIAL INJURY:** To avoid the risk of fire or electrical shock, use only the power cord provided with this product or the manufacturer's authorized replacement.



**CAUTION—POTENTIAL INJURY:** Do not use this product with extension cords, multioutlet power strips, multioutlet extenders, or UPS devices. The power capacity of these types of accessories can be easily overloaded by a laser printer and may result in a risk of fire, property damage, or poor printer performance.



**CAUTION—POTENTIAL INJURY:** To reduce the risk of fire, use only a 26 AWG or larger telecommunications (RJ-11) cord when connecting this product to the public switched telephone network. For users in Australia, the cord must be approved by the Australian Communications and Media Authority.




**CAUTION—POTENTIAL INJURY:** Only a Lexmark Inline Surge Protector that is properly connected between the printer and the power cord provided with the printer may be used with this product. The use of non-Lexmark surge protection devices may result in a risk of fire, property damage, or poor printer performance.





**CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, do not place or use this product near water or wet locations.





**CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, do not set up this product or make any electrical or cabling connections, such as the power cord, fax feature, or telephone, during a lightning storm.


 **CAUTION—POTENTIAL INJURY:** Do not cut, twist, bind, crush, or place heavy objects on the power cord. Do not subject the power cord to abrasion or stress. Do not pinch the power cord between objects such as furniture and walls. If any of these things happen, a risk of fire or electrical shock results. Inspect the power cord regularly for signs of such problems. Remove the power cord from the electrical outlet before inspecting it.


 **CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, make sure that all external connections (such as Ethernet and telephone system connections) are properly installed in their marked plug-in ports.

 **CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, if you are accessing the controller board or installing optional hardware or memory devices sometime after setting up the printer, then turn the printer off, and unplug the power cord from the electrical outlet before continuing. If you have any other devices attached to the printer, then turn them off as well, and unplug any cables going into the printer.


 **CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, do not use the fax feature during a lightning storm.







 **CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock when cleaning the exterior of the printer, unplug the power cord from the electrical outlet and disconnect all cables from the printer before proceeding.

 **CAUTION—POTENTIAL INJURY:** The printer weight is greater than 18 kg (40 lb) and requires two or more trained personnel to lift it safely.

 **CAUTION—POTENTIAL INJURY:** When moving the printer, follow these guidelines to avoid personal injury or printer damage:

- Make sure that all doors and trays are closed.
- Turn off the printer, and then unplug the power cord from the electrical outlet.
- Disconnect all cords and cables from the printer.
- If the printer has separate floor-standing optional trays or output options attached to it, then disconnect them before moving the printer.
- If the printer has a caster base, then carefully roll it to the new location. Use caution when passing over thresholds and breaks in flooring.
- If the printer does not have a caster base but is configured with optional trays or output options, then remove the output options and lift the printer off the trays. Do not try to lift the printer and any options at the same time.
- Always use the handholds on the printer to lift it.
- Any cart used to move the printer must have a surface able to support the full footprint of the printer.
- Any cart used to move the hardware options must have a surface able to support the dimensions of the options.
- Keep the printer in an upright position.
- Avoid severe jarring movements.
- Make sure that your fingers are not under the printer when you set it down.
- Make sure that there is adequate clearance around the printer.

 **CAUTION—TIPPING HAZARD:** Installing one or more options on your printer or MFP may require a caster base, furniture, or other feature to prevent instability causing possible injury. For more information on supported configurations, see [www.lexmark.com/multifunctionprinters](http://www.lexmark.com/multifunctionprinters).

-  **CAUTION—TIPPING HAZARD:** To reduce the risk of equipment instability, load each tray separately. Keep all other trays closed until needed.
-  **CAUTION—HOT SURFACE:** The inside of the printer might be hot. To reduce the risk of injury from a hot component, allow the surface to cool before touching it.
-  **CAUTION—PINCH HAZARD:** To avoid the risk of a pinch injury, use caution in areas marked with this label. Pinch injuries may occur around moving parts, such as gears, doors, trays, and covers.
-  **CAUTION—ROTATING FAN BLADES:** To avoid the risk of laceration from moving fan blades, turn off the printer and unplug the power cord from the electrical outlet before accessing areas marked with this symbol.
-  **CAUTION—POTENTIAL INJURY:** This product uses a laser. Use of controls or adjustments or performance of procedures other than those specified in the *User's Guide* may result in hazardous radiation exposure.
-  **CAUTION—POTENTIAL INJURY:** The lithium battery in this product is not intended to be replaced. There is a danger of explosion if a lithium battery is incorrectly replaced. Do not recharge, disassemble, or incinerate a lithium battery. Discard used lithium batteries according to the manufacturer's instructions and local regulations.

This equipment is not suitable for use in locations where children are likely to be present.

This product is designed, tested, and approved to meet strict global safety standards with the use of specific manufacturer's components. The safety features of some parts may not always be obvious. The manufacturer is not responsible for the use of other replacement parts.

Refer service or repairs, other than those described in the user documentation, to a service representative.


This product uses a printing process that heats the print media, and the heat may cause the media to release emissions. You must understand the section in your operating instructions that discusses the guidelines for selecting print media to avoid the possibility of harmful emissions.


This product may produce small amounts of ozone during normal operation, and may be equipped with a filter designed to limit ozone concentrations to levels well below the recommended exposure limits. To avoid high ozone concentration levels during extensive usage, install this product in a well-ventilated area and replace the ozone and exhaust filters if instructed to do so in the product maintenance instructions. If there are no references to filters in the product maintenance instructions, then there are no filters requiring replacement for this product.

**SAVE THESE INSTRUCTIONS.**

# Learning about the printer

## Finding information about the printer


What are you looking for?	Find it here
Initial setup instructions: <ul style="list-style-type: none"> <li>Connecting the printer</li> <li>Installing the printer software</li> </ul>	See the setup documentation that came with the printer or go to <a href="http://support.lexmark.com">http://support.lexmark.com</a> .
More setup and instructions for using the printer: <ul style="list-style-type: none"> <li>Selecting and storing paper and specialty media</li> <li>Loading paper</li> <li>Configuring printer settings</li> <li>Viewing and printing documents and photos</li> <li>Setting up and using the printer software</li> <li>Configuring the printer on a network</li> <li>Caring for and maintaining the printer</li> <li>Troubleshooting and solving problems</li> </ul>	<p><i>Information Center</i>—Go to <a href="http://infoserve.lexmark.com">http://infoserve.lexmark.com</a>.</p> <p><i>Help Menu Pages</i>—Access the guides on the printer firmware or go to <a href="http://support.lexmark.com">http://support.lexmark.com</a>.</p> <p><i>Touch Screen Guide</i>—Go to <a href="http://support.lexmark.com">http://support.lexmark.com</a>.</p> <p>Product videos—Go to <a href="http://infoserve.lexmark.com/idv/">http://infoserve.lexmark.com/idv/</a>.</p>
Information on setting up and configuring the accessibility features of your printer	<i>Lexmark Accessibility Guide</i> —Go to <a href="http://support.lexmark.com">http://support.lexmark.com</a> .
Help using the printer software	<p>Help for Microsoft® Windows® or Macintosh operating systems—Open a printer software program or application, and then click <b>Help</b>.</p> <p>Click  to view context-sensitive information.</p> <p><b>Notes:</b></p> <ul style="list-style-type: none"> <li>Help is automatically installed with the printer software.</li> <li>Depending on the operating system, the printer software is located in the printer program folder or on the desktop.</li> </ul>


What are you looking for?	Find it here
<p>The latest supplemental information, updates, and customer support:</p> <ul style="list-style-type: none"> <li>• Documentation</li> <li>• Driver downloads</li> <li>• Live chat support</li> <li>• E-mail support</li> <li>• Voice support</li> </ul>	<p>Go to <a href="http://support.lexmark.com">http://support.lexmark.com</a>.</p> <p><b>Note:</b> Select your country or region, and then select your product to view the appropriate support site.</p> <p>Support contact information for your country or region can be found on the website or on the printed warranty that came with the printer.</p> <p>Have the following information ready when you contact customer support:</p> <ul style="list-style-type: none"> <li>• Place and date of purchase</li> <li>• Machine type and serial number</li> </ul> 
<ul style="list-style-type: none"> <li>• Safety information</li> <li>• Regulatory information</li> <li>• Warranty information</li> <li>• Environmental information</li> </ul>	<p>Warranty information varies by country or region:</p> <ul style="list-style-type: none"> <li>• <b>In the U.S.</b>—See the Statement of Limited Warranty included with the printer, or go to <a href="http://support.lexmark.com">http://support.lexmark.com</a>.</li> <li>• <b>In other countries and regions</b>—See the printed warranty that came with the printer.</li> </ul> <p><i>Product Information Guide</i>—See the documentation that came with the printer or go to <a href="http://support.lexmark.com">http://support.lexmark.com</a>.</p>

## Selecting a location for the printer

When selecting a location for the printer, leave enough room to open trays, covers, and doors and to install hardware options.

- Set up the printer near an electrical outlet.

 **CAUTION—POTENTIAL INJURY:** To avoid the risk of fire or electrical shock, connect the power cord to an appropriately rated and properly grounded electrical outlet that is near the product and easily accessible.

 **CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, do not place or use this product near water or wet locations.


- Make sure that airflow in the room meets the latest revision of the ASHRAE 62 standard or the CEN Technical Committee 156 standard.
- Provide a flat, sturdy, and stable surface.

- Keep the printer:
  - Clean, dry, and free of dust.
  - Away from stray staples and paper clips.
  - Away from the direct airflow of air conditioners, heaters, or ventilators.
  - Free from direct sunlight and humidity extremes.

- Observe the recommended temperatures and avoid fluctuations:

Ambient temperature	10 to 32.2°C (50 to 90°F)
Storage temperature	-40 to 43.3°C (-40 to 110°F)

- Allow the following recommended amount of space around the printer for proper ventilation:




1	Top	330 mm (13 in.)
2	Right side	152 mm (6 in.)
3	Front	381 mm (15 in.)
4	Left side	457 mm (18 in.)
5	Rear	203 mm (8 in.)

## Printer configurations

**Note:** Make sure to configure the printer on a flat, sturdy, and stable surface.




## Basic model




1	Automatic document feeder (ADF)
2	Control panel
3	Standard bin
4	Standard 550-sheet tray
5	Multipurpose feeder
6	Proximity sensor <b>Note:</b> This feature is available only in some printer units.

## Configured model

 **CAUTION—TIPPING HAZARD:** Installing one or more options on your printer or MFP may require a caster base, furniture, or other feature to prevent instability causing possible injury. For more information on supported configurations, see [www.lexmark.com/multifunctionprinters](http://www.lexmark.com/multifunctionprinters).

You can configure your printer by adding an optional 2200-sheet tray or a combination of up to three optional 550-sheet trays or envelope trays.




1	Staple finisher <b>Note:</b> This option is not supported if another finisher is installed.
2	Multiposition staple, hole punch finisher <b>Note:</b> This option is not supported if another finisher is installed.
3	Mailbox
4	Optional 2200-sheet tray
5	Caster base
6	Optional 550-sheet trays or envelope trays

## Attaching cables


- CAUTION—POTENTIAL INJURY:** To avoid the risk of fire or electrical shock, connect the power cord to an appropriately rated and properly grounded electrical outlet that is near the product and easily accessible.
- CAUTION—POTENTIAL INJURY:** To avoid the risk of fire or electrical shock, use only the power cord provided with this product or the manufacturer's authorized replacement.
- CAUTION—POTENTIAL INJURY:** To avoid the risk of electrical shock, do not set up this product or make any electrical or cabling connections, such as the power cord, fax feature, or telephone, during a lightning storm.
- CAUTION—POTENTIAL INJURY:** To reduce the risk of fire, use only a 26 AWG or larger telecommunications (RJ-11) cord when connecting this product to the public switched telephone network. For users in Australia, the cord must be approved by the Australian Communications and Media Authority.

**Warning—Potential Damage:** To avoid loss of data or printer malfunction, do not touch the USB cable, any wireless network adapter, or the printer in the areas shown while actively printing.



	Use the	To
<b>1</b>	EXT port	Connect additional devices (telephone or answering machine) to the printer and the telephone line. Use this port if you do not have a dedicated fax line for the printer and if this connection method is supported in your country or region. <b>Note:</b> Remove the plug to access the port.
<b>2</b>	LINE port	Connect the printer to an active telephone line through a standard wall jack (RJ-11), DSL filter, VoIP adapter, or any other adapter that allows you to access the telephone line to send and receive faxes.
<b>3</b>	USB printer port	Connect the printer to a computer.
<b>4</b>	Ethernet port	Connect the printer to an Ethernet network.
<b>5</b>	USB ports	Attach a keyboard or any compatible options.
<b>6</b>	Power cord socket	Connect the printer to a properly grounded electrical outlet.

## Using the control panel



	Use the	To
<b>1</b>	Display	<ul style="list-style-type: none"> <li>View the printer messages and supply status.</li> <li>Set up and operate the printer.</li> </ul>
<b>2</b>	Home button	Go to the home screen.
<b>3</b>	Power button	<ul style="list-style-type: none"> <li>Turn on or turn off the printer.</li> </ul> <p><b>Note:</b> To turn off the printer, press and hold the power button for five seconds.</p> <ul style="list-style-type: none"> <li>Set the printer to Sleep or Hibernate mode.</li> <li>Wake the printer from Sleep or Hibernate mode.</li> </ul>
<b>4</b>	Keypad	Enter numbers or symbols in an input field.
<b>5</b>	Pause button	Place a dial pause in a fax number.
<b>6</b>	Start button	Start a job, depending on which mode is selected.
<b>7</b>	Volume buttons	Adjust the volume of the headset or speaker.
<b>8</b>	Indicator light	Check the status of the printer.
<b>9</b>	Headset or speaker port	Attach a headset or speaker.
<b>10</b>	Stop or Cancel button	Stop the current job.
<b>11</b>	Clear all or Reset button	Reset the default settings of a function such as copying, faxing, or scanning.
<b>12</b>	Backspace button	Move the cursor backward and delete a character in an input field.

# Understanding the status of the power button and indicator light


Indicator light	Printer status
Off	The printer is off or in Hibernate mode.
Blue	The printer is ready or processing data.
Red	The printer requires user intervention.

Power button light	Printer status
Off	The printer is off, ready, or processing data.
Solid amber	The printer is in sleep mode.
Blinking amber	The printer is in hibernate mode.

# Using the home screen

**Note:** Your home screen may vary depending on your home screen customization settings, administrative setup, and active embedded solutions.



Touch	To
1	Copy Make copies.
2	E-mail Send e-mails.
3	Change Language Change the language on the printer display.
4	Fax Send fax.
5	Settings Access the printer menus.
6	Held Faxes Show all the current held fax jobs. <b>Note:</b> If Held Faxes is hidden, then Release Held Faxes appears.
7	Shortcut Center Organize all shortcuts.

Touch	To
<b>8</b> Status/Supplies	<ul style="list-style-type: none"> <li>Show a printer warning or error message whenever the printer requires intervention to continue processing.</li> <li>View more information on the printer warning or message, and on how to clear it.</li> </ul> <p><b>Note:</b> You can also access this setting by touching the top section of the home screen.</p>
<b>9</b> Address Book	Access, create, and organize contacts.
<b>10</b> Scan Profiles	Scan and save documents directly to the computer.
<b>11</b> FTP	Scan and save documents directly to an FTP server.
<b>12</b> Bookmarks	Organize all bookmarks.
<b>13</b> Held Jobs	Show all the current held print jobs
<b>14</b> USB Drive	View, select, or print photos and documents from a flash drive.
<b>15</b> Job Queue	<p>Show all the current print jobs.</p> <p><b>Note:</b> You can also access this setting by touching the top section of the home screen.</p>

### These settings may also appear on the home screen

Touch	To
App Profiles	Access application profiles.
Lock Device	Prevent users from accessing any printer functions from the home screen.

## Menu map

### Device

<ul style="list-style-type: none"> <li>Preferences</li> <li>Remote Operator Panel</li> <li>Notifications</li> <li>Power Management</li> <li>Information Sent to Lexmark</li> </ul>	<ul style="list-style-type: none"> <li>Accessibility</li> <li>Restore Factory Defaults</li> <li>Maintenance</li> <li>Visible Home Screen Icons</li> <li>About This Printer</li> </ul>
--	---

### Print

<ul style="list-style-type: none"> <li>Layout</li> <li>Finishing</li> <li>Setup</li> <li>Quality</li> <li>Job Accounting</li> <li>XPS</li> </ul>	<ul style="list-style-type: none"> <li>PDF</li> <li>PostScript</li> <li>PCL</li> <li>HTML</li> <li>Image</li> <li>PPDS</li> </ul>
--	---

## Paper

- |  |   |
|--|---|
| <ul style="list-style-type: none"><li>• Tray Configuration</li><li>• Media Configuration</li></ul> | <ul style="list-style-type: none"><li>• Bin Configuration</li></ul> |
|--|---|

## Copy

Copy Defaults

## Fax

- |   |  |
|---|--|
| <ul style="list-style-type: none"><li>• Fax Mode</li><li>• Analog Fax Setup</li></ul> | <ul style="list-style-type: none"><li>• Fax Server Setup</li></ul> |
|---|--|

## E-mail

- |  |  |
|--|--|
| <ul style="list-style-type: none"><li>• E-mail Setup</li><li>• E-mail Defaults</li></ul> | <ul style="list-style-type: none"><li>• Web Link Setup</li></ul> |
|--|--|

## Network/Ports

- |  |   |
|--|---|
| <ul style="list-style-type: none"><li>• Network Overview</li><li>• Wireless</li><li>• AirPrint</li><li>• Ethernet</li><li>• TCP/IP</li><li>• IPv6</li><li>• SNMP</li><li>• IPSec</li></ul> | <ul style="list-style-type: none"><li>• LPD Configuration</li><li>• HTTP/FTP Settings</li><li>• ThinPrint</li><li>• USB</li><li>• Parallel [x]</li><li>• Serial</li><li>• Google Cloud Print</li><li>• Wi-Fi Direct</li></ul> |
|--|---|

## FTP

FTP Defaults

## USB Drive

- |  |   |
|--|---|
| <ul style="list-style-type: none"><li>• Flash Drive Scan</li></ul> | <ul style="list-style-type: none"><li>• Flash Drive Print</li></ul> |
|--|---|

## Security

- |   |  |
|---|--|
| <ul style="list-style-type: none"><li>• Login Methods</li><li>• Schedule USB Devices</li><li>• Security Audit Log</li><li>• Login Restrictions</li><li>• Confidential Print Setup</li></ul> | <ul style="list-style-type: none"><li>• Disk Encryption</li><li>• Erase Temporary Data Files</li><li>• Solutions LDAP Settings</li><li>• Miscellaneous</li></ul> |
|---|--|

## Option Card Menu

**Note:** This setting appears only when an optional card is installed.

## Reports

<ul style="list-style-type: none"><li>• Menu Settings Page</li><li>• Device</li><li>• Print</li></ul>	<ul style="list-style-type: none"><li>• Shortcuts</li><li>• Fax</li><li>• Network</li></ul>
---	---

## Help

<ul style="list-style-type: none"><li>• Print All Guides</li><li>• Color Quality Guide</li><li>• Connection Guide</li><li>• Copy Guide</li><li>• E-mail Guide</li><li>• Fax Guide</li></ul>	<ul style="list-style-type: none"><li>• Information Guide</li><li>• Media Guide</li><li>• Moving Guide</li><li>• Print Quality Guide</li><li>• Scan Guide</li><li>• Supplies Guide</li></ul>
---	--

## Troubleshooting

<ul style="list-style-type: none"><li>• Basic Print Quality Samples</li></ul>	<ul style="list-style-type: none"><li>• Advanced Print Quality Samples</li></ul>
---	--

# Printing a menu settings page

From the home screen, touch **Settings > Reports > Menu Settings Page**.



# Setting up and using the home screen applications

## Customizing the home screen

- 1 Open a web browser, and then type the printer IP address in the address field.

**Notes:**

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.
- If you are using a proxy server, then temporarily disable it to load the web page correctly.

- 2 Click **Settings > Device > Visible Home Screen Icons**.

- 3 Select the icons that you want to appear on the home screen.

- 4 Apply the changes.

## Setting up Forms and Favorites

- 1 Open a Web browser, and then type the printer IP address in the address field.

**Notes:**

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.

- 2 Click **Apps > Forms and Favorites > Configure**.

- 3 Click **Add**, and then customize the settings.

**Notes:**

- To make sure that the location settings of the bookmark are correct, type the IP address of the host computer where the bookmark is located.
- Make sure that the printer has access rights to the folder where the bookmark is located.

- 4 Apply the changes.

## Setting up Card Copy

- 1 Open a Web browser, and then type the printer IP address in the address field.

**Notes:**

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.

- 2 Click **Apps > Card Copy > Configure**.

### 3 Configure the output options and scan settings.

**Notes:**

- When scanning a card, make sure that the scan resolution does not exceed 200 dpi for color and 400 dpi for black and white.
- When scanning multiple cards, make sure that the scan resolution does not exceed 150 dpi for color and 300 dpi for black and white.
- You need a printer hard disk to scan multiple cards.
- Make sure that the printer network and e-mail settings are configured.

### 4 Apply the changes.

## Using Shortcut Center

- 1 From the home screen, touch **Shortcut Center**, and then select a printer function.
- 2 Touch **Create Shortcut**, and then configure the settings.
- 3 Touch **Save**, and then type a unique shortcut name.
- 4 Apply the changes.

## Setting up Scan Center

- 1 From the home screen, touch **Scan Center**.
- 2 Select and create a destination, and then configure the settings.

**Notes:**

- When creating a network destination, make sure to validate and adjust the settings until no errors occur.
- Only destinations created from the Embedded Web Server are saved. For more information, see the documentation that came with the solution.

### 3 Apply the changes.

## Using Customer Support

- 1 From the home screen, touch **Customer Support**.
- 2 Print or e-mail the information.

**Note:** For information on configuring the application settings, see the *Customer Support Administrator's Guide*.

## Setting up Device Quotas

You may need administrative rights to access the application.

- 1 Open a Web browser, and then type the printer IP address in the address field.

**Notes:**

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.

**2** Click **Apps > Device Quotas > Configure**.

**3** From the User Accounts section, add or edit a user, and then set the user quota.

**4** Apply the changes.

**Note:** For information on how to configure the application and its security settings, see the *Device Quotas Administrator's Guide*.

## Using QR Code Generator

You may need administrative rights to access the application.

**1** Open a Web browser, and then type the printer IP address in the address field.

**Notes:**

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.

**2** Click **Apps > QR Code Generator > Configure**.

**3** Do either of the following:

- Select a default QR code value.
- Type a QR code value.

**4** Apply the changes.

## Using Google Drive

### Scanning a document

**Notes:**

- Make sure that the printer is connected to your Google account.
- Make sure that you have installed a printer hard disk.

**1** Load an original document into the ADF tray or on the scanner glass.

**2** From the home screen, touch **Google Drive**.


**3** If prompted, type your user credentials.

**4** Select a destination folder.

**5** Scan the document, and then follow the instructions on the display.

## Printing a document

**Note:** Make sure that the printer is connected to your Google account.

- 1 From the home screen, touch **Google Drive**.
- 2 If prompted, type your user credentials.
- 3 Touch  beside the document.
- 4 Print the document.

**Note:** For information on how to configure the printer for the application, see the *Google Drive Administrator's Guide*.

## Using Display Customization

### Changing the wallpaper

- 1 From the home screen, touch **Change Wallpaper**.
- 2 Select an image to use.
- 3 Apply the changes.

### Creating a slide show

Before you begin, make sure to configure the slide show settings. For more information, see the documentation that came with the solution.

- 1 Insert a flash drive into the USB port.
- 2 From the home screen, touch **Slideshow**.

**Note:** Images appear in alphabetical order.

## Configuring Eco-Settings

- 1 From the home screen, touch **Eco-Settings**.
- 2 Configure the Eco-Mode settings or schedule a power-saving mode.
- 3 Apply the changes.

## Managing contacts

### Adding contacts

- 1 Open a web browser, and then type the printer IP address in the address field.

**Notes:**

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.

- If you are using a proxy server, then temporarily disable it to load the web page correctly.

**2** Click **Address Book**.

**3** From the Contacts section, add a contact.

**Note:** You can assign the contact to one or more groups.

**4** If necessary, specify a login method to allow application access.

**5** Apply the changes.

## Adding groups

**1** Open a web browser, and then type the printer IP address in the address field.

**Notes:**

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.
- If you are using a proxy server, then temporarily disable it to load the web page correctly.

**2** Click **Address Book**.

**3** From the Contact Groups section, add a group name.

**Note:** You can assign one or more contacts to the group.

**4** Apply the changes.

## Editing contacts or groups

**1** Open a web browser, and then type the printer IP address in the address field.

**Notes:**

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.
- If you are using a proxy server, then temporarily disable it to load the web page correctly.

**2** Click **Address Book**.

**3** Do either of the following:

- From the Contacts section, click a contact name, and then edit the information.
- From the Contact Groups section, click a group name, and then edit the information.

**4** Apply the changes.

## Deleting contacts or groups

**1** Open a web browser, and then type the printer IP address in the address field.

**Notes:**

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.

- If you are using a proxy server, then temporarily disable it to load the web page correctly.

**2** Click **Address Book**.

**3** Do either of the following:

- From the Contacts section, select a contact that you want to delete.
- From the Contact Groups section, select a group name that you want to delete.

# Setting up and using the accessibility features

## Enabling Magnification mode

- 1 From the control panel, press and hold the **5** key until you hear a voice message.
- 2 Select **Magnification**.
- 3 Select **OK**.

For more information on navigating a magnified screen, see [“Navigating the screen using gestures” on page 28](#).

## Activating Voice Guidance

### From the control panel

- 1 Press and hold the **5** key until you hear a voice message.
- 2 Select **OK**.

### From the keyboard

- 1 Press and hold the **5** key until you hear a voice message.
- 2 Press **Tab** to navigate the focus cursor to the OK button, and then press **Enter**.

### Notes:

- Voice Guidance is also activated when you insert headphones into the headphone jack.
- To adjust the volume, use the volume buttons at the bottom part of the control panel.

## Adjusting the Voice Guidance speech rate

- 1 From the home screen, select **Settings** > **Device** > **Accessibility** > **Speech Rate**.
- 2 Select the speech rate.

## Enabling spoken passwords or personal identification numbers

- 1 From the home screen, select **Settings** > **Device** > **Accessibility** > **Speak Passwords/PINs**.
- 2 Enable the setting.

## Navigating the screen using gestures

### Notes:

- The gestures are applicable only when Voice Guidance is activated.
- A physical keyboard is required for typing characters and adjusting certain settings.

Gesture	Function
Double-tap	Select an option or item on the screen.
Triple-tap	Zoom in or zoom out text and images.
Swipe right or swipe down	Move to the next item on the screen.
Swipe left or swipe up	Move to the previous item on the screen.
Pan	Access parts of the zoomed image that are beyond the limits of the screen. <b>Note:</b> This gesture requires the use of two fingers to drag across a zoomed image.
Swipe up then left	Exit an application and return to the home screen.
Swipe down then left	<ul style="list-style-type: none"><li>• Cancel a job.</li><li>• Go back to the previous setting.</li><li>• Exit the screen that appears without changing any setting or value.</li></ul>
Swipe up then down	Repeat a spoken prompt.

## Using the keyboard on the display

Do one or more of the following:

- Drag a finger over the key to announce the character.
- Lift the finger to enter or type the character in the field.
- Press **Backspace** to delete characters.
- To hear the content in the input field, press **Tab**, and then press **Shift + Tab**.



# Loading paper and specialty media

## Setting the size and type of the specialty media


The trays automatically detect the size of plain paper. For specialty media like labels, card stock, or envelopes, do the following:

- 1 From the home screen, navigate to:  
**Settings > Paper > Tray Configuration > Paper Size/Type** > select a paper source
- 2 Set the size and type of the specialty media.

## Configuring Universal paper settings

- 1 From the home screen, touch **Settings > Paper > Media Configuration > Universal Setup**.
- 2 Configure the settings.

## Loading trays

 **CAUTION—TIPPING HAZARD:** To reduce the risk of equipment instability, load each tray separately. Keep all other trays closed until needed.


- 1 Pull out the tray.

**Note:** To avoid paper jams, do not remove trays while the printer is busy.




- 2 Adjust the guides to match the size of the paper that you are loading.

**Note:** Use the indicators on the bottom of the tray to position the guides.



**3** Flex, fan, and align the paper edges before loading.




**4** Load the paper with the printable side faceup.

**Note:** Load envelopes only in the optional envelope tray.

**Warning—Potential Damage:** Do not use envelopes with stamps, clasps, snaps, windows, coated linings, or self-stick adhesives in the optional envelope tray.

**Notes:**

- Load letterhead faceup with the header on the left side of the tray for one-sided printing.
- Load letterhead facedown with the header on the right side of the tray for two-sided printing.
- Load letterhead faceup with the header on the right side of the tray for one-sided print jobs that require finishing.
- Load letterhead facedown with the header on the left side of the tray for two-sided print jobs that require finishing.
- Load pre-punched paper with the holes toward the front or left side of the tray.
- Load envelopes with the flap side down and against the back side of the tray. Load European envelopes with the flap side down and against the left side of the tray.
- Do not slide paper into the tray.
- Make sure that the stack height is below the maximum paper fill indicator. Overfilling may cause paper jams.



**5** Insert the tray.


If loading a paper type other than plain, set the paper size and paper type in the Paper menu to match the paper loaded.

## Loading the multipurpose feeder


**1** Open the multipurpose feeder.



**2** Adjust the guide to match the size of the paper you are loading.




**3** Flex, fan, and align the paper edges before loading.




#### 4 Load the paper.

- Load paper, card stock, and transparencies with the printable side facedown and the top edge entering the printer first.



- Load envelopes with the flap side up and against the left side of the paper guide. Load European envelopes with the flap side up and entering the printer first.



**Warning—Potential Damage:** Do not use envelopes with stamps, clasps, snaps, windows, coated linings, or self-stick adhesives.

#### 5 From the control panel, set the paper size and type to match the paper loaded in the tray.

## Linking trays

#### 1 Open a Web browser, and then type the printer IP address in the address field.

##### Notes:

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.

#### 2 Click **Settings** > **Paper**.

#### 3 Match the paper size and type for the trays you are linking.


**Note:** To unlink trays, make sure that no trays have the same paper size or type.

#### 4 Save the settings.

**Note:** You can also change the paper size and type settings from the printer control panel.

**Warning—Potential Damage:** The temperature of the fuser varies according to the specified paper type. To avoid printing issues, match the paper type settings in the printer with the paper loaded in the tray.

# Printing

 **CAUTION—PINCH HAZARD:** To avoid the risk of a pinch injury, use caution in areas marked with this label. Pinch injuries may occur around moving parts, such as gears, doors, trays, and covers.

## Printing from a computer

**Note:** For labels, card stock, and envelopes, set the paper size and type in the printer before printing the document.

- 1 From the document that you are trying to print, open the Print dialog.
- 2 If necessary, adjust the settings.
- 3 Print the document.

## Printing forms

- 1 From the home screen, navigate to:  
**Forms and Favorites** > select form > **Print**
- 2 If necessary, configure the print settings.
- 3 Send the print job.

## Printing from a mobile device

### Printing from a mobile device using Lexmark Mobile Print

Lexmark™ Mobile Print allows you to send documents and images directly to a supported Lexmark printer.

- 1 Open the document, and then send or share the document to Lexmark Mobile Print.  
**Note:** Some third-party applications may not support the send or share feature. For more information, see the documentation that came with the application.
- 2 Select a printer.
- 3 Print the document.

### Printing from a mobile device using Google Cloud Print

Google Cloud Print™ is a mobile printing service that allows enabled applications on mobile devices to print to any Google Cloud Print-ready printer.

- 1 From the home screen of your mobile device, launch an enabled application.
- 2 Tap **Print**, and then select a printer.
- 3 Print the document.

## Printing from a mobile device using Mopria Print Service

Mopria® Print Service is a mobile printing solution for mobile devices running on Android version 4.4 or later. It allows you to print directly to any Mopria-certified printer.

**Note:** Before printing, make sure that the Mopria Print Service is enabled.

- 1 From the home screen of your mobile device, launch a compatible application.
- 2 Tap **Print**, and then select a printer.
- 3 Print the document.

## Printing from a mobile device using AirPrint


AirPrint is a mobile printing solution that allows you to print directly from Apple devices to an AirPrint-certified printer.

**Note:** This application is supported only in some Apple devices.

- 1 From the home screen of your mobile device, launch a compatible application.
- 2 Select an item to print, and then tap the share icon.
- 3 Tap **Print**, and then select the printer.
- 4 Send the print job.

## Printing from a flash drive

- 1 Insert a flash drive into the USB port.



### Notes:

- If you insert the flash drive when an error message appears, then the printer ignores the flash drive.
- If you insert the flash drive while the printer is processing other print jobs, then **Busy** appears on the display.

- 2 From the display, touch the document that you want to print.

If necessary, configure other print settings.

- 3 Send the print job.

To print another document, touch **USB Drive**.

**Warning—Potential Damage:** Do not touch the printer or the flash drive in the area shown while actively printing, reading, or writing from the memory device. Loss of data or a malfunction can occur.



## Supported flash drives and file types

### Flash drives

- Lexar JumpDrive S70 (16GB and 32GB)
- SanDisk Cruzer (16GB and 32GB)
- PNY Attaché (16GB and 32GB)

### Notes:

- The printer supports high-speed USB flash drives with full-speed standard.
- USB flash drives must support the File Allocation Table (FAT) system.

### File types

Documents:

- .doc or .docx
- .xls or .xlsx
- .ppt or .pptx
- .pdf
- .xps

Images:

- .dcx
- .gif
- .jpeg or .jpg
- .bmp
- .pcx
- .tiff or .tif
- .png

## Configuring confidential jobs

- 1 From the home screen, touch **Settings** > **Security** > **Confidential Print Setup**.
- 2 Configure the settings.

Use	To
Max Invalid PIN	Limit the number of times an invalid PIN can be entered. <b>Note:</b> When the limit is reached, the print jobs for that user name are deleted.
Confidential Job Expiration	Set the amount of time before confidential jobs are automatically deleted from the printer memory. <b>Note:</b> Confidential held jobs are stored in the printer until you log in and release or delete them manually.
Repeat Job Expiration	Set the amount of time before repeat jobs are deleted from the printer memory. <b>Note:</b> Repeat held jobs are stored so extra copies can be printed later.
Verify Job Expiration	Set the amount of time before verify jobs are deleted from the printer memory. <b>Note:</b> Verify jobs print one copy to check if it is satisfactory before printing the remaining copies.
Reserve Job Expiration	Set the amount of time before reserved jobs are deleted without being printed. <b>Note:</b> Reserve held jobs are automatically deleted after printing.

## Printing held jobs

- 1 From the document you are trying to print, open the Print dialog.
- 2 Select the printer, and then do the following:
  - For Windows users, click **Properties** or **Preferences**, and then click **Print and Hold**.
  - For Macintosh users, select **Print and Hold**.
- 3 Select the print job type.
- 4 If necessary, assign a user name.
- 5 Send the print job.
- 6 From the printer home screen, touch **Held Jobs**.
- 7 Send the print job.



## Printing a font sample list

- 1 From the home screen, touch **Settings** > **Reports** > **Print** > **Print Fonts**.
- 2 Touch **PCL Fonts** or **PostScript Fonts**.

## Printing a directory list

From the home screen, touch **Settings** > **Reports** > **Print** > **Print Directory**.

## Canceling a print job

### From the printer control panel

- 1 From the home screen, touch **Job Queue**.  
**Note:** You can also access this setting by touching the top section of the home screen.
- 2 Select the job to cancel.

### From the computer

- 1 Depending on the operating system, do either of the following:
  - Open the printers folder, and then select your printer.
  - From the System Preferences in the Apple menu, navigate to your printer.
- 2 Select the job to cancel.

# Copying

## Making copies

- 1 Load an original document into the ADF tray or on the scanner glass.

**Note:** To avoid a cropped image, make sure that the original document and output have the same paper size.

- 2 From the home screen, touch **Copy**, and then specify the number of copies.

If necessary, adjust the copy settings.

- 3 Copy the document.

**Note:** To make a quick copy, from the control panel, press .

## Copying photos

- 1 Place a photo on the scanner glass.
- 2 From the home screen, touch **Copy** > **Content** > **Photo**.
- 3 From the Content Source menu, select the setting that best matches the original photo.
- 4 Send the copy job.

## Copying on letterhead

- 1 Load an original document into the ADF tray or on the scanner glass.
- 2 From the home screen, touch **Copy**, and then specify the size of the original document.
- 3 Touch **Copy to**, and then select the tray that contains the specialty media.  
If you are loading the specialty media into the multipurpose feeder, then navigate to:  
**Multipurpose Feeder** > select the size of the specialty media > **Letterhead**
- 4 Send the copy job.

## Copying on both sides of the paper

- 1 Load an original document into the ADF tray or on the scanner glass.
- 2 From the home screen, touch **Copy** > **Paper Setup**.
- 3 Adjust the settings.
- 4 Copy the document.

## Reducing or enlarging copies

- 1 Load an original document into the ADF tray or on the scanner glass.
- 2 From the home screen, navigate to:  
**Copy** > **Scale** > specify a scale value  
**Note:** Changing the size of the original document or output after setting Scale restores the scale value to Auto.
- 3 Copy the document.

## Collating copies

- 1 Load an original document into the ADF tray or on the scanner glass.
- 2 From the home screen, touch **Copy**, and then set Collate to **On**.
- 3 Copy the document.


## Placing separator sheets between copies

- 1 Load an original document into the ADF tray or on the scanner glass.
- 2 From the home screen, touch **Copy** > **Separator Sheets**.
- 3 Adjust the settings.
- 4 Send the copy job.

## Copying multiple pages onto a single sheet

- 1 Load an original document into the ADF tray or on the scanner glass.
- 2 From the home screen, touch **Copy** > **Pages per Side**.
- 3 Adjust the settings.
- 4 Copy the document.

## Creating a copy shortcut

- 1 From the home screen, touch **Copy**.
- 2 Adjust the settings, and then touch .
- 3 Enter a shortcut name.
- 4 Apply the changes.

# E-mailing

## Setting up the e-mail function

- 1 From the home screen, touch **Settings > Device > Preferences > Run Initial Setup**.
- 2 Turn off the printer, wait for about 10 seconds, and then turn it back on.
- 3 From the Before You Begin screen, select **Change the Settings and Continue with the Wizard**.
- 4 From the Fax/Email Server Setup screen, enter the needed information.
- 5 Finish the setup.

## Configuring e-mail settings

- 1 Open a Web browser, and then type the printer IP address in the address field.

**Notes:**

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.

- 2 Click **Settings > E-mail**.
- 3 Enter the needed information.
- 4 Apply the changes.

## Sending an e-mail

### Using the control panel


- 1 Load an original document into the ADF tray or on the scanner glass.
- 2 From the home screen, touch **E-mail**, and then enter the needed information.

**Note:** You can also enter the recipient using the address book or shortcut number.
- 3 If necessary, configure the output file type settings.
- 4 Send the e-mail.

### Using the shortcut number

- 1 From the control panel, press **#**, and then enter the shortcut number using the keypad.
- 2 Send the e-mail.

## Creating an e-mail shortcut

- 1 From the home screen, touch **E-mail**.
- 2 Configure the settings, and then touch .
- 3 Enter a shortcut name.
- 4 Apply the changes.

# Faxing

## Setting up the printer to fax

### Notes:

- The following connection methods are applicable only in some countries or regions.
- During the initial printer setup, clear the fax function check box and any other function you plan to set up later, and then touch **Continue**.
- The indicator light may blink red if the fax function is enabled and not fully set up.

**Warning—Potential Damage:** Do not touch cables or the printer in the area shown while actively sending or receiving a fax.



## Setting up the fax function


- 1 From the home screen, touch **Settings > Device > Preferences > Run Initial Setup**.
- 2 Turn off the printer, wait for about 10 seconds, and then turn it back on.
- 3 From the Before You Begin screen, select **Change the Settings and Continue with the Wizard**.
- 4 From the Fax/Email Server Setup screen, enter the needed information.
- 5 Finish the setup.

## Setting up fax using a standard telephone line

**⚠ CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, do not set up this product or make any electrical or cabling connections, such as the power cord, fax feature, or telephone, during a lightning storm.

**⚠ CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, do not use the fax feature during a lightning storm.

### Setup 1: Printer is connected to a dedicated fax line



- 1 Connect one end of the telephone cable to the line port of the printer.
- 2 Connect the other end of the telephone cable to an active analog wall jack.


#### Notes:

- You can set the printer to receive faxes automatically (Auto Answer On) or manually (Auto Answer Off).
- If you want to receive faxes automatically, then set the printer to pick up on any number of rings that you want.

## Setup 2: Printer is sharing the line with an answering machine


**Note:** If you subscribe to a distinctive ring service provided by your telephone company, then make sure that you set the correct ring pattern for the printer. Otherwise, the printer does not receive faxes even if you have set it to receive faxes automatically.

### Connected to the same telephone wall jack



- 1 Connect one end of the telephone cable to the line port of the printer.
- 2 Connect the other end of the telephone cable to an active analog wall jack.
- 3 Connect the answering machine to the telephone port of the printer.




**Connected to different wall jacks**

- 1** Connect one end of the telephone cable to the line port of the printer.
- 2** Connect the other end of the telephone cable to an active analog wall jack.

**Notes:**

- If you have only one telephone number on your line, then set the printer to receive faxes automatically.
- Set the printer to pick up calls two rings after the answering machine. For example, if the answering machine picks up calls after four rings, then set the printer Rings to Answer setting to six.

**Setup 3: Printer is sharing the line with a telephone subscribed to voice mail service**

- 1** Connect one end of the telephone cable to the line port of the printer.
- 2** Connect the other end of the telephone cable to an active analog wall jack.
- 3** Connect the telephone to the telephone port of the printer.


**Notes:**

- This setup works best if you are using voice mail more often than fax, and if you subscribe to a distinctive ring service.
- When you answer the telephone and you hear fax tones, press **\*9\*** or the manual answer code on the telephone to receive the fax.
- You can also set the printer to receive faxes automatically, but turn off the voice mail service when you are expecting a fax.

## Setting up fax using digital subscriber line

**⚠ CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, do not set up this product or make any electrical or cabling connections, such as the power cord, fax feature, or telephone, during a lightning storm.

**⚠ CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, do not use the fax feature during a lightning storm.



Digital subscriber line (DSL) splits your regular telephone line into two channels: voice and Internet. Telephone and fax signals travel through the voice channel, and internet signals pass through the other channel.

Install a DSL filter to minimize interference between the two channels and ensure a quality connection.


**Note:** Contact your DSL provider to obtain a DSL filter.

- 1 Connect the line port of the DSL filter to the wall jack.
- 2 Connect one end of the telephone cable to the line port of the printer. Connect the other end to the phone port on the DSL filter.
- 3 To connect a telephone to the printer, remove any installed adapter plug from the telephone port of the printer, and then connect the telephone.

## Setting up fax using VoIP telephone service

**CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, do not set up this product or make any electrical or cabling connections, such as the power cord, fax feature, or telephone, during a lightning storm.

**CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, do not use the fax feature during a lightning storm.



- 1 Connect one end of the telephone cable to the line port of the printer.
- 2 Connect the other end of the cable to the port labeled **Phone Line 1** or **Phone Port** on the VoIP adapter.

**Note:** The port labeled **Phone Line 2** or **Fax Port** is not always active. VoIP providers may charge extra cost for the activation of the second phone port.

- 3 Connect the telephone to the telephone port of the printer.

**Notes:**

- To check if the telephone port on the VoIP adapter is active, plug an analog telephone into the port, and then listen for a dial tone.
- If you need two phone ports for your devices, but do not want to pay extra cost, then use a phone splitter. Plug the phone splitter into the port labeled **Phone Line 1** or **Phone Port**, and then plug the printer and telephone into the splitter.
- To check the splitter, plug an analog telephone into the splitter, and then listen for a dial tone.

## Setting up fax using cable modem connection




**CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, do not set up this product or make any electrical or cabling connections, such as the power cord, fax feature, or telephone, during a lightning storm.



**CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, do not use the fax feature during a lightning storm.


### Setup 1: Printer is connected directly to a cable modem



- 1 Connect one end of the telephone cable to the line port of the printer.
- 2 Connect the other end of the cable to the port labeled **Phone Line 1** or **Phone Port** on the cable modem.
- 3 Connect your analog telephone to the telephone port of the printer.

**Note:** To check if the telephone port on the cable modem is active, connect an analog telephone, and then listen for a dial tone.


## Setup 2: Printer is connected to a wall jack; cable modem is installed elsewhere in the facility



- 1 Connect one end of the telephone cable to the line port of the printer.
- 2 Connect the other end of the telephone cable to an active analog telephone wall jack.
- 3 Connect your analog telephone to the telephone port of the printer.


## Setting up fax in countries or regions with different telephone wall jacks and plugs

**⚡ CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, do not set up this product or make any electrical or cabling connections, such as the power cord, fax feature, or telephone, during a lightning storm.

 **CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, do not use the fax feature during a lightning storm.

The standard wall jack adopted by most countries or regions is RJ11. If the wall jack or equipment in your facility is not compatible with this type of connection, then use a telephone adapter. An adapter for your country or region may not come with your printer, and you may need to purchase it separately.


There may be an adapter plug installed in the telephone port of the printer. Do not remove the adapter plug from the telephone port of the printer if you are connecting to a serial or cascaded telephone system.



Part name	Part number
Lexmark adapter plug	40X8519




## Connecting the printer to a non-RJ11 wall jack



- 1 Connect one end of the telephone cable to the line port of the printer.
- 2 Connect the other end of the cable to the RJ11 adapter, and then connect the adapter to the wall jack.
- 3 If you want to connect another device with a non-RJ11 connector to the same wall jack, then connect it directly to the telephone adapter.

## Connecting the printer to a wall jack in Germany

The German wall jack has two kinds of ports. The N ports are for fax machines, modems, and answering machines. The F port is for telephones. Connect the printer to any of the N ports.



- 1 Connect one end of the telephone cable to the line port of the printer.
- 2 Connect the other end of the telephone cable to the RJ11 adapter, and then connect the adapter to an N port.
- 3 If you want to connect a telephone and answering machine to the same wall jack, then connect the devices as shown.

## Connecting to a distinctive ring service

A distinctive ring service lets you have multiple telephone numbers on one telephone line. Each telephone number is assigned a different ring pattern.

- 1 From the home screen, touch **Settings > Fax > Analog Fax Setup > Fax Receive Settings > Admin Controls > Answer On**.
- 2 Select the ring pattern.
- 3 Apply the changes.

## Setting the fax date and time

- 1 From the home screen, touch **Settings > Device > Preferences > Date and Time > Configure**.
- 2 Configure the settings.

## Configuring daylight saving time

- 1 From the home screen, touch **Settings > Device > Preferences > Date and Time > Configure**.
- 2 In the Time Zone menu, select **Custom**.
- 3 Configure the settings.

## Sending a fax

### Using the control panel

- 1 Load the original document into the ADF tray or on the scanner glass.
- 2 From the home screen, touch **Fax**, and then enter the needed information.
- 3 If necessary, configure other fax settings.
- 4 Send the fax job.

### Using the computer

#### For Windows users

- 1 With a document open, click **File > Print**.
- 2 Select the printer, and then click **Properties, Preferences, Options, or Setup**.
- 3 Click **Fax > Enable fax**, and then enter the recipient number.
- 4 If necessary, configure other fax settings.
- 5 Send the fax job.

### For Macintosh users

- 1 With a document open, choose **File > Print**.
- 2 Select the printer and enter the recipient number.
- 3 If necessary, configure other fax settings.
- 4 Send the fax job.


## Scheduling a fax

- 1 Load the original document into the ADF tray or on the scanner glass.
- 2 From the home screen, navigate to:  
**Fax > enter the fax number > Send Time**
- 3 Configure the date and time to send the fax.
- 4 If necessary, configure other fax settings.
- 5 Send the fax job.

## Creating a fax destination shortcut

- 1 From the home screen, touch **Fax > To**.
- 2 Enter the recipient number.

**Note:** To create a group of fax numbers, touch , and then enter another fax number.

- 3 Touch .
- 4 Enter a shortcut name.
- 5 Apply the changes.

## Changing the fax resolution

- 1 Load an original document into the ADF tray or on the scanner glass.
- 2 From the home screen, touch **Fax**, and then enter the needed information.
- 3 Adjust the Resolution setting.
- 4 Send the fax job.

## Adjusting the fax darkness

- 1 Load an original document into the ADF tray or on the scanner glass.
- 2 From the home screen, touch **Fax**, and then enter the needed information.

- 3 Adjust the Darkness setting.
- 4 Send the fax job.

## Viewing a fax log

- 1 Open a Web browser, and then type the printer IP address in the address field.

**Notes:**

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.
- If you are using a proxy server, then temporarily disable it to load the Web page correctly.

- 2 Click **Settings > Reports > Fax**.
- 3 Click **Fax Job Log** or **Fax Call Log**.

## Blocking junk faxes

- 1 From the home screen, touch **Settings > Fax > Analog Fax Setup > Fax Receive Settings > Admin Controls > Block No Name Fax**.
- 2 Apply the changes.

## Holding faxes

- 1 From the home screen, touch **Settings > Fax > Analog Fax Setup > Fax Receive Settings > Holding Faxes**.
- 2 Select a mode.

## Forwarding a fax


- 1 From the home screen, touch **Settings > Fax > Analog Fax Setup > Fax Receive Settings > Admin Controls**.
- 2 Configure the Fax Forwarding, Forward To, and Forward to Shortcut settings.
- 3 Apply the changes.

## Scanning

### Scanning to an FTP server


- 1 Load the original document into the ADF tray or on the scanner glass.
- 2 From the home screen, touch **FTP**, and then enter the needed information.
- 3 If necessary, configure other FTP settings.
- 4 Send the FTP job.

### Creating an FTP shortcut

- 1 From the home screen, touch **FTP**.
- 2 Enter the FTP server address, and then touch .
- 3 Enter a shortcut name.
- 4 Apply the changes.

### Scanning to a flash drive

- 1 Load an original document into the ADF tray or on the scanner glass.
- 2 Insert the flash drive.



- 3 Touch **Scan to USB** and adjust the settings if necessary.

**Note:** If the USB Drive screen does not appear, then touch **USB Drive** on the home screen.

- 4 Scan the document.

**Warning—Potential Damage:** To avoid loss of data or printer malfunction, do not touch the flash drive or the printer in the area shown while actively printing, reading, or writing from the memory device.



## Sending scanned documents to a computer

- 1 Load an original document into the ADF tray or on the scanner glass.
- 2 From the home screen, touch **Scan Profiles** > **Scan To Computer**.
- 3 Select the scan profile where you want to save the document.

## Securing the printer

### Locating the security slot

The printer is equipped with a security lock feature. Attach a security lock compatible with most laptop computers in the location shown to secure the printer in place.



### Erasing printer memory

To erase volatile memory or buffered data in your printer, turn off the printer.

To erase non-volatile memory or individual settings, device and network settings, security settings, and embedded solutions, do the following:

- 1 From the home screen, touch **Settings > Device > Maintenance > Out of Service Erase**.
- 2 Select the **Sanitize all information on nonvolatile memory** check box, and then touch **ERASE**.
- 3 Follow the instructions on the display.

### Erasing printer hard disk memory

- 1 From the home screen, touch **Settings > Device > Maintenance > Out of Service Erase**.
- 2 Select the **Sanitize all information on hard disk** check box, and then touch **ERASE**.
- 3 Follow the instructions on the display.

**Note:** This process can take from several minutes to more than an hour, making the printer unavailable for other tasks.



## Configuring printer hard disk encryption

- 1 From the home screen, touch **Settings** > **Security** > **Disk Encryption** > **Start Encryption**.

**Note:** Enabling disk encryption erases the contents of the hard disk. If necessary, back up important data from the printer before starting the encryption.

- 2 Follow the instructions on the display.

**Notes:**

- Do not turn off the printer during the encryption process. Loss of data can occur.
- Disk encryption can take from several minutes to more than an hour, making the printer unavailable for other tasks.
- After encryption, the printer returns to the home screen.

## Restoring factory default settings

From the home screen, touch **Settings** > **Device** > **Restore Factory Defaults** > **Restore Settings** > **Restore all settings** > **RESTORE** > **Start**.

For more information, see [“Erasing printer memory” on page 60](#).

## Statement of Volatility

Your printer contains various types of memory that can store device and network settings, and user data.

Type of memory	Description
Volatile memory	Your printer uses standard <i>random access memory</i> (RAM) to temporarily buffer user data during simple print jobs.
Non-volatile memory	Your printer may use two forms of non-volatile memory: EEPROM and NAND (flash memory). Both types are used to store the operating system, device settings, network information and bookmark settings, and embedded solutions.
Hard disk memory	Some printers have a hard disk drive installed. The printer hard disk is designed for printer-specific functionality. This lets the printer retain buffered user data from complex print jobs, as well as form data, and font data.

Erase the content of any installed printer memory in the following circumstances:

- The printer is being decommissioned.
- The printer hard disk is being replaced.
- The printer is being moved to a different department or location.
- The printer is being serviced by someone from outside your organization.
- The printer is being removed from your premises for service.
- The printer is being sold to another organization.

## Disposing of a printer hard disk

**Note:** Some printer models may not have a printer hard disk installed.

In high-security environments, it may be necessary to take additional steps to make sure that confidential data stored in the printer hard disk cannot be accessed when the printer—or its hard disk—is removed from your premises.

- **Degaussing**—Flushes the hard disk with a magnetic field that erases stored data
- **Crushing**—Physically compresses the hard disk to break component parts and render them unreadable
- **Milling**—Physically shreds the hard disk into small metal bits

**Note:** Most data can be erased electronically, but the only way to guarantee that all data are completely erased is to physically destroy each hard disk where data is stored.

# Maintaining the printer

**Warning—Potential Damage:** Failure to maintain optimum printer performance, or to replace parts and supplies, may cause damage to your printer.

## Adjusting the speaker volume

### Adjusting the default internal speaker volume

The speaker volume will reset to default value after the session is logged out, when the printer wakes from Sleep or Hibernate mode, or after a power-on reset.

1 From the control panel, navigate to:

**Settings > Device > Preferences > Audio Feedback**

2 Select the volume.

**Note:** If Quiet Mode is enabled, then audible alerts are turned off.

### Adjusting the default headphones volume

Headphones volume will reset to default value after the session is logged out, when the printer wakes from Sleep or Hibernate mode, or after a power-on reset.

1 From the control panel, select **Settings > Device > Accessibility > Headphone Volume**.

2 Select the volume.

## Configuring the fax speaker settings

**Note:** This feature is available only in some printer models.

1 From the home screen, select **Settings > Fax > Analog Fax Setup > Speaker Settings**.

2 Do the following:

- Set the Speaker Mode to **Always On**.
- Set the Speaker Volume to **High**.
- Activate the Ringer Volume.

## Networking

### Connecting the printer to a wireless network using Wi-Fi Protected Setup (WPS)

Before you begin, make sure that:

- The access point (wireless router) is WPS-certified or WPS-compatible. For more information, see the documentation that came with your access point.
- A wireless network adapter is installed in your printer. For more information, see the instructions that came with the adapter.

#### Using the Push Button method

- 1 From the control panel, navigate to:  
**Settings > Network/Ports > Wireless > Wi-Fi Protected Setup > Start Push Button Method**
- 2 Follow the instructions on the display.

#### Using the personal identification number (PIN) method

- 1 From the control panel, navigate to:  
**Settings > Network/Ports > Wireless > Wi-Fi Protected Setup > Start PIN Method**
- 2 Copy the eight-digit WPS PIN.
- 3 Open a Web browser, and then type the IP address of your access point in the address field.

##### Notes:

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.
  - If you are using a proxy server, then temporarily disable it to load the Web page correctly.
- 4 Access the WPS settings. For more information, see the documentation that came with your access point.
  - 5 Enter the eight-digit PIN, and then save the changes.

### Changing port settings after installing an internal solutions port

#### Notes:

- If the printer has a static IP address, then do not change the configuration.
- If the computers are configured to use the network name instead of an IP address, then do not change the configuration.
- If you are adding a wireless internal solutions port (ISP) to a printer previously configured for an Ethernet connection, then disconnect the printer from the Ethernet network.

#### For Windows users

- 1 Open the printers folder.
- 2 From the shortcut menu of the printer with the new ISP, open the printer properties.

- 3 Configure the port from the list.
- 4 Update the IP address.
- 5 Apply the changes.

#### For Macintosh users

- 1 From System Preferences in the Apple menu, navigate to the list of printers, and then select + > IP.
- 2 Type the IP address in the address field.
- 3 Apply the changes.

## Setting up serial printing (Windows only)


- 1 Set the parameters in the printer.
  - a From the control panel, navigate to the menu for the port settings.
  - b Locate the menu for the serial port settings, and then adjust the settings, if necessary.
  - c Apply the changes.
- 2 From your computer, open the printers folder, and then select your printer.
- 3 Open the printer properties, and then select the COM port from the list.
- 4 Set the COM port parameters in Device Manager.

#### Notes:

- Serial printing reduces printing speed.
- Make sure that the serial cable is connected to the serial port on your printer.

## Cleaning printer parts

### Cleaning the printer

 **CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock when cleaning the exterior of the printer, unplug the power cord from the electrical outlet and disconnect all cables from the printer before proceeding.


#### Notes:

- Perform this task after every few months.
  - Damage to the printer caused by improper handling is not covered by the printer warranty.
- 1 Turn off the printer, and then unplug the power cord from the electrical outlet.
  - 2 Remove paper from the standard bin and multipurpose feeder.
  - 3 Remove any dust, lint, and pieces of paper around the printer using a soft brush or vacuum.
  - 4 Wipe the outside of the printer with a damp, soft, lint-free cloth.

**Notes:**

- Do not use household cleaners or detergents, as they may damage the finish of the printer.
- Make sure that all areas of the printer are dry after cleaning.

**5** Connect the power cord to the electrical outlet, and then turn on the printer.


 **CAUTION—POTENTIAL INJURY:** To avoid the risk of fire or electrical shock, connect the power cord to an appropriately rated and properly grounded electrical outlet that is near the product and easily accessible.

## Cleaning the scanner glass

**1** Open the scanner cover.



**2** Wipe the areas shown with a damp, soft, lint-free cloth.



<b>1</b>	White underside of the scanner cover
<b>2</b>	Scanner glass
<b>3</b>	Automatic document feeder (ADF) glass
<b>4</b>	White underside of the ADF cover



**3** Close the scanner cover.

## Emptying the hole punch box


- 1 Open door J.



- 2 Remove and empty the hole punch box.



- 3 Insert the hole punch box.



- 4 Close door J.

## Ordering parts and supplies

To order parts and supplies in the U.S., contact 1-800-539-6275 for information about Lexmark authorized supplies dealers in your area. In other countries or regions, go to [www.lexmark.com](http://www.lexmark.com) or contact the place where you purchased the printer.

**Note:** All life estimates for printer supplies assume printing on letter- or A4-size plain paper.

## Checking the status of parts and supplies

- 1 From the home screen, touch **Status/Supplies**.
- 2 Select the parts or supplies that you want to check.

**Note:** You can also access this setting by touching the top section of the home screen.

## Using genuine Lexmark parts and supplies

Your Lexmark printer is designed to function best with genuine Lexmark parts and supplies. Use of third-party supplies or parts may affect the performance, reliability, or life of the printer and its imaging components. It can also affect warranty coverage. Damage caused by the use of third-party parts and supplies is not covered by the warranty. All life indicators are designed to function with Lexmark parts and supplies, and may deliver unpredictable results if third-party parts and supplies are used. Imaging component usage beyond the intended life may damage your Lexmark printer or its associated components.

## Ordering toner cartridges

**Note:** Extremely low print coverage for extended periods of time may negatively affect actual yield and may cause cartridge parts to fail before toner exhaustion.



Item	Worldwide
<b>BSD</b>	
Black	24B6511
Cyan	24B6508
Magenta	24B6509
Yellow	24B6510
<b>BSD LAD</b>	
Black	24B2454
Cyan	24B2154
Magenta	24B2155
Yellow	24B2421

Item	Worldwide
<b>BSD</b>	
Black	24B6515
Cyan	24B6512
Magenta	24B6513
Yellow	24B6514
<b>BSD LAD</b>	
Black	24B4803
Cyan	24B2455
Magenta	24B3581
Yellow	24B3587

## Ordering a photoconductor unit

Item	Part number
Photoconductor unit (1 pack)	72K0P00
Photoconductor unit (3 pack)	72K0Q00

## Ordering developer units

Item	Part number
<b>Return Program developer units</b>	
Black developer unit	72K0DK0
Color (CMY) developer kit	72K0DV0
Cyan developer unit	72K0DC0

Item	Part number
Magenta developer unit	72K0DM0
Yellow developer unit	72K0DY0
<b>Regular developer units</b>	
Black developer unit	72K0D10
Color (CMY) developer kit	72K0D50
Cyan developer unit	72K0D20
Magenta developer unit	72K0D30
Yellow developer unit	72K0D40

## Ordering imaging units

Item	All countries and regions
<b>Return Program imaging units</b>	
Black imaging unit	21K3401
Cyan imaging unit	21K3403
Magenta imaging unit	21K3402
Yellow imaging unit	21K3404

## Ordering staple cartridges

Item	Part number
Staple cartridges	25A0013

## Ordering a waste toner bottle

Item	Part number
Waste toner bottle	72K0W00

## Configuring supply notifications

- 1 Open a web browser, and then type the printer IP address in the address field.

### Notes:

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.
- If you are using a proxy server, then temporarily disable it to load the web page correctly.

- 2 Click **Settings > Device > Notifications**.

- 3 From the Supplies menu, click **Custom Supply Notifications**.

- 4 Select a notification for each supply item.
- 5 Apply the changes.


## Replacing parts and supplies

### Replacing a developer unit


- 1 Open door B.






**CAUTION—HOT SURFACE:** The inside of the printer might be hot. To reduce the risk of injury from a hot component, allow the surface to cool before touching it.




- 2 Open door A.




**3** Remove the waste toner bottle.**4** Remove the imaging unit.**5** Remove the developer unit.**6** Unpack the new developer unit, and then remove the packing material.


**7** Insert the new developer unit.



**8** Insert the imaging unit.



**9** Insert the waste toner bottle.



**10** Close doors A and B.


## Replacing the fuser

**1** Turn off the printer.


**2** Open door B.



**CAUTION—HOT SURFACE:** The inside of the printer might be hot. To reduce the risk of injury from a hot component, allow the surface to cool before touching it.




**3** Remove the fuser.




**4** Unpack the new fuser.

**5** Clean the fuser lens using the cotton swab that came with the package.



- 6 Insert the new fuser until it *clicks* into place.



- 7 Close door B.


- 8 Turn on the printer.

## Replacing a photoconductor unit


- 1 Open door B.




**CAUTION—HOT SURFACE:** The inside of the printer might be hot. To reduce the risk of injury from a hot component, allow the surface to cool before touching it.





**2** Open door A.



**3** Remove the waste toner bottle.








**4** Remove the imaging unit.**5** Remove the photoconductor unit.**6** Unpack the new photoconductor unit, and then remove the packing material.


**Warning—Potential Damage:** Do not expose the photoconductor unit to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems.

**Warning—Potential Damage:** Do not touch the photoconductor drum. Doing so may affect the print quality of future print jobs.


**7** Insert the new photoconductor unit.

**8** Insert the imaging unit.**9** Insert the waste toner bottle.**10** Close doors A and B.**Replacing an imaging unit****1** Open door B.


**CAUTION—HOT SURFACE:** The inside of the printer might be hot. To reduce the risk of injury from a hot component, allow the surface to cool before touching it.




**2** Open door A.




**3** Remove the waste toner bottle.




**4** Remove the imaging unit.**5** Unpack the new imaging unit, and then remove the packing material.

**Warning—Potential Damage:** Do not expose the photoconductor unit to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems.

**Warning—Potential Damage:** Do not touch the photoconductor drum. Doing so may affect the print quality of future print jobs.

**6** Insert the new imaging unit.


- 7** Insert the waste toner bottle.



- 8** Close doors A and B.

## Replacing a toner cartridge

- 1** Open door A.




- 2** Remove the toner cartridge.



- 3** Unpack the new toner cartridge.

- 4 Insert the new toner cartridge until it *clicks* into place.





- 5 Close door A.

## Replacing the pick roller


### Replacing the pick roller in the 550-sheet tray or envelope tray

- 1 Turn off the printer.
- 2 Remove the tray.




**3** Remove the pick roller.**4** Unpack the new pick roller.

**5** Insert the new pick roller until it *clicks* into place.



**6** Insert the tray.




**7** Turn on the printer.





## Replacing the pick roller in the 2200-sheet tray

- 1 Turn off the printer.
- 2 Pull out, and then unlock the tray.




- 3 Remove the tray.
- 4 Remove the pick roller.




- 5 Unpack the new pick roller.

**6** Insert the new pick roller until it *clicks* into place.




**7** Insert the tray.




**8** Turn on the printer.

## Replacing the separator bracket

- 1 Pull out the tray.




- 2 Remove the separator bracket.



- 3 Unpack the new separator bracket.


- 4 Insert the new separator bracket until it *clicks* into place.




- 5 Insert the tray.

## Replacing the waste toner bottle

1 Open door A.




2 Remove the waste toner bottle.



3 Unpack the new waste toner bottle.

4 Insert the new waste toner bottle.



5 Close door A.


## Replacing the transfer belt

1 Turn off the printer.


2 Open door B.




**CAUTION—HOT SURFACE:** The inside of the printer might be hot. To reduce the risk of injury from a hot component, allow the surface to cool before touching it.




3 Open door A.




#### 4 Remove the waste toner bottle.



#### 5 Open door A1.



#### 6 Remove the transfer belt.




- 7** Unpack the new transfer belt, and then remove the packing material.

**Warning—Potential Damage:** Do not expose the transfer belt to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems.


**Warning—Potential Damage:** Do not touch the transfer belt. Doing so may affect the print quality of future print jobs.




- 8** Insert the new transfer belt until it *clicks* into place.



- 9** Close door A1.



- 10 Insert the waste toner bottle.



- 11 Close doors A and B.


- 12 Turn on the printer.

## Replacing the transfer roller


- 1 Open door B.



**CAUTION—HOT SURFACE:** The inside of the printer might be hot. To reduce the risk of injury from a hot component, allow the surface to cool before touching it.



- 2 Remove the transfer roller.






**3** Unpack the new transfer roller.

**Note:** Do not remove the white packing material.

**4** Insert the new transfer roller.




**5** Remove the white packing material.




**6** Close door B.

## Replacing the ADF pick roller

- 1 Turn off the printer.
- 2 Open door D.




- 3 Remove the ADF pick roller cover.



- 4 Remove the ADF pick roller.


**Warning—Potential Damage:** Some parts of the printer are easily damaged by static electricity. Before touching any parts or components in an area marked with the static-sensitive symbol, touch a metal surface in an area away from the symbol.




5 Unpack the new ADF pick roller.

6 Insert the new ADF pick roller until it *clicks* into place.

**Warning—Potential Damage:** Some parts of the printer are easily damaged by static electricity. Before touching any parts or components in an area marked with the static-sensitive symbol, touch a metal surface in an area away from the symbol.



7 Insert the ADF pick roller cover until it *clicks* into place.




8 Close door D.


9 Turn on the printer.

## Replacing the ADF feed roller

- 1 Turn off the printer.
- 2 Open door D.




- 3 Remove the ADF pick roller cover.




- 4 Remove the ADF feed roller.

**Warning—Potential Damage:** Some parts of the printer are easily damaged by static electricity. Before touching any parts or components in an area marked with the static-sensitive symbol, touch a metal surface in an area away from the symbol.




**5** Unpack the new ADF feed roller.

**6** Insert the new ADF feed roller until it *clicks* into place.



**7** Insert the ADF pick roller cover until it *clicks* into place.




**8** Close door D.

**9** Turn on the printer.

## Replacing the ADF separator roller

- 1 Turn off the printer.
- 2 Open door D.




- 3 Remove the ADF separator roller cover.




- 4 Remove the ADF separator roller.


**Warning—Potential Damage:** Some parts of the printer are easily damaged by static electricity. Before touching any parts or components in an area marked with the static-sensitive symbol, touch a metal surface in an area away from the symbol.



- 5 Unpack the new ADF separator roller.
- 6 Insert the new ADF separator roller until it *clicks* into place.



- 7 Insert the ADF separator roller cover until it *clicks* into place.




- 8 Close door D.
- 9 Turn on the printer.



## Replacing the staple cartridge unit

### Replacing the staple cartridge in the staple finisher

- 1 Open door C.






**2** Open door G.**3** Remove the staple cartridge.**4** Unpack the new staple cartridge.



- 5 Insert the new staple cartridge until it *clicks* into place.




- 6 Close doors G and C.




**CAUTION—PINCH HAZARD:** To avoid the risk of a pinch injury, keep hands clear of the labeled area when closing door C.

## Replacing the staple cartridge holder in the staple finisher


- 1 Open door C.





**2** Open door G.




**3** Pull out the staple cartridge holder.



**4** Remove the staple cartridge.**5** Unpack the new staple cartridge holder.**6** Insert the staple cartridge until it *clicks* into place.

- 7 Insert the staple cartridge holder until it *clicks* into place.



- 8 Close doors G and C.



**CAUTION—PINCH HAZARD:** To avoid the risk of a pinch injury, keep hands clear of the labeled area when closing door C.


## Replacing the staple cartridge in the multiposition staple, hole punch finisher

- 1 Open door J.




- 2 Remove the staple cartridge.

**Note:** If necessary, remove the tape from the staple cartridge holder.



**3** Unpack the new staple cartridge.

**4** Insert the new staple cartridge until it *clicks* into place.




**5** Close door J.

## Replacing the staple cartridge holder in the multiposition staple, hole punch finisher


- 1 Open door J.



- 2 Remove the staple cartridge holder.




- 3 Remove the staple cartridge.




- 4 Unpack the new staple cartridge holder.

**5** Insert the staple cartridge until it *clicks* into place.



**6** Insert the staple cartridge holder until it *clicks* into place.



**7** Close door J.

## Storing supplies


Choose a cool, clean storage area for the printer supplies. Store supplies right side up in their original packing until you are ready to use them.


Do not expose supplies to:


- Direct sunlight
- Temperatures above 35°C (95°F)
- High humidity above 80%
- Salty air
- Corrosive gases
- Heavy dust

## Moving the printer

### Moving the printer to another location

 **CAUTION—POTENTIAL INJURY:** The printer weight is greater than 18 kg (40 lb) and requires two or more trained personnel to lift it safely.

 **CAUTION—POTENTIAL INJURY:** To avoid the risk of fire or electrical shock, use only the power cord provided with this product or the manufacturer's authorized replacement.

 **CAUTION—POTENTIAL INJURY:** When moving the printer, follow these guidelines to avoid personal injury or printer damage:

- Make sure that all doors and trays are closed.
- Turn off the printer, and then unplug the power cord from the electrical outlet.
- Disconnect all cords and cables from the printer.
- If the printer has a caster base, then carefully roll it to the new location. Use caution when passing over thresholds and breaks in flooring.
- If the printer does not have a caster base but is configured with optional trays, then lift the printer off the trays. Do not try to lift the printer and the trays at the same time.
- Always use the handholds on the printer to lift it.
- Any cart used to move the printer must have a surface able to support the full footprint of the printer.
- Any cart used to move the hardware options must have a surface able to support the dimensions of the options.
- Keep the printer in an upright position.
- Avoid severe jarring movements.
- Make sure that your fingers are not under the printer when you set it down.
- Make sure that there is adequate clearance around the printer.

**Note:** Damage to the printer caused by improper moving is not covered by the printer warranty.

### Shipping the printer

For shipping instructions, go to <http://support.lexmark.com> or contact customer support.

## Saving energy and paper

### Setting up power saver modes

#### Eco-Mode

- 1 From the home screen, touch **Settings > Device > Power Management > Eco-Mode**.
- 2 Select a setting.



## Sleep mode

- 1 From the home screen, touch **Settings > Device > Power Management > Timeouts > Sleep Mode**.
- 2 Enter the number of minutes the printer stays idle before it enters Sleep mode.

## Hibernate mode

- 1 From the home screen, touch **Settings > Device > Power Management > Timeouts > Hibernate Timeout**.
- 2 Select the amount of time before the printer enters hibernate mode.

### Notes:

- Make sure to wake the printer from hibernate mode before sending a print job.
- The Embedded Web Server is disabled when the printer is in hibernate mode.

## Adjusting the brightness of the printer display

- 1 From the home screen, touch **Settings > Device > Preferences > Screen Brightness**.
- 2 Adjust the setting.

## Conserving supplies

- Print on both sides of the paper.  
**Note:** Two-sided printing is the default setting in the print driver.
- Print multiple pages on a single sheet of paper.
- Use the preview feature to see how the document looks like before printing it.
- Print one copy of the document to check its content and format for accuracy.

## Disabling the proximity sensor

**Note:** This feature is available only in some printer units.

From the home screen, touch **Settings > Power Management > Timeouts > Disabled**.

To keep the sensor running, do the following:

- Remove any obstructions within 1.5 m (5 ft.).
- Remove other devices that interfere with the sensor.

# Recycling

## Recycling Lexmark products

To return Lexmark products for recycling:

- 1 Go to [www.lexmark.com/recycle](http://www.lexmark.com/recycle).
- 2 Select the product you want to recycle.

**Note:** Printer supplies and hardware not listed in the Lexmark Collection and Recycling Program may be recycled through your local recycling center.

## Recycling Lexmark packaging

Lexmark continually strives to minimize packaging. Less packaging helps to ensure that Lexmark printers are transported in the most efficient and environmentally sensitive manner and that there is less packaging to dispose of. These efficiencies result in fewer greenhouse emissions, energy savings, and natural resource savings. Lexmark also offers recycling of packaging components in some countries or regions. For more information, go to [www.lexmark.com/recycle](http://www.lexmark.com/recycle), and then choose your country or region. Information on available packaging recycling programs is included with the information on product recycling.

Lexmark cartons are 100% recyclable where corrugated recycling facilities exist. Facilities may not exist in your area.

The foam used in Lexmark packaging is recyclable where foam recycling facilities exist. Facilities may not exist in your area.

When you return a cartridge to Lexmark, you can reuse the box that the cartridge came in. Lexmark recycles the box.

## Returning Lexmark cartridges for reuse or recycling

The Lexmark Cartridge Collection Program allows you to return used cartridges for free to Lexmark for reuse or recycling. One hundred percent of the empty cartridges returned to Lexmark are either reused or demanufactured for recycling. The boxes used to return the cartridges are also recycled.

To return Lexmark cartridges for reuse or recycling, do the following:


- 1** Go to [www.lexmark.com/recycle](http://www.lexmark.com/recycle).
- 2** Select the product that you want to recycle.

# Clearing jams


## Avoiding jams

### Load paper properly

- Make sure that the paper lies flat in the tray.



- Do not load or remove a tray while the printer is printing.
- Do not load too much paper. Make sure that the stack height is below the maximum paper fill indicator.
- Do not slide paper into the tray. Load paper as shown in the illustration.




- Make sure that the paper guides are positioned correctly and are not pressing tightly against the paper or envelopes.
- Push the tray firmly into the printer after loading paper.

### Use recommended paper

- Use only recommended paper or specialty media.
- Do not load paper that is wrinkled, creased, damp, bent, or curled.

- Flex, fan, and align the paper edges before loading.




- Do not use paper that has been cut or trimmed by hand.
- Do not mix paper sizes, weights, or types in the same tray.
- Make sure that the paper size and type are set correctly on the computer or printer control panel.
- Store paper according to manufacturer recommendations.

## Identifying jam locations

### Notes:

- When Jam Assist is set to On, the printer flushes blank pages or pages with partial prints after a jammed page has been cleared. Check your printed output for blank pages.
- When Jam Recovery is set to On or Auto, the printer reprints jammed pages.


### Basic model



	Jam locations
<b>1</b>	Multipurpose feeder
<b>2</b>	Duplex unit
<b>3</b>	Fuser

	Jam locations
<b>4</b>	Automatic document feeder (ADF)
<b>5</b>	Standard bin
<b>6</b>	Door G
<b>7</b>	Door F
<b>8</b>	Trays

## Configured model



	Jam locations
<b>1</b>	Door L
<b>2</b>	Door J
<b>3</b>	Door K
<b>4</b>	Door N

## Paper jam in trays

- 1 Pull out the tray.



- 2 Remove the jammed paper.

**Note:** Make sure that all paper fragments are removed.




- 3 Insert the tray.

- 4 Open the tray cover.



- 5 Remove the jammed paper.

**Note:** Make sure that all paper fragments are removed.




- 6 Close the tray cover.

## Paper jam in the multipurpose feeder

- 1 Remove paper from the multipurpose feeder.
- 2 Remove the jammed paper.


**Note:** Make sure that all paper fragments are removed.



- 3 Open door B, and then remove any paper fragments.




**CAUTION—HOT SURFACE:** The inside of the printer might be hot. To reduce the risk of injury from a hot component, allow the surface to cool before touching it.



4 Close door B.

5 Flex, fan, and align the paper edges before loading.




6 Reload paper.

## Paper jam in the automatic document feeder

1 Remove all original documents from the ADF tray.

2 Open door D.




3 Remove the jammed paper.

**Note:** Make sure that all paper fragments are removed.



**Warning—Potential Damage:** Some parts of the printer are easily damaged by static electricity. Before touching any parts or components in an area marked with the static-sensitive symbol, touch a metal surface in an area away from the symbol.




**4** Close door D.

**5** Open the scanner cover.




**6** Open door E.



- 7 Remove the jammed paper.

**Note:** Make sure that all paper fragments are removed.




- 8 Close door E and the scanner cover.

## Paper jam in the standard bin

- 1 Remove the jammed paper.


**Note:** Make sure that all paper fragments are removed.



- 2 Open door B, and then remove any paper fragments.



**CAUTION—HOT SURFACE:** The inside of the printer might be hot. To reduce the risk of injury from a hot component, allow the surface to cool before touching it.



**3** Close door B.


## Paper jam in door B

### Paper jam in the fuser

**1** Open door B.




**CAUTION—HOT SURFACE:** The inside of the printer might be hot. To reduce the risk of injury from a hot component, allow the surface to cool before touching it.




**2** Remove the jammed paper.

**Note:** Make sure that all paper fragments are removed.




**3** Open the fuser access door.



**4** Remove the jammed paper.

**Note:** Make sure that all paper fragments are removed.




- 5 Close door B.

### Paper jam in the duplex unit

- 1 Open door B.




**CAUTION—HOT SURFACE:** The inside of the printer might be hot. To reduce the risk of injury from a hot component, allow the surface to cool before touching it.




- 2 Remove the jammed paper.

**Note:** Make sure that all paper fragments are removed.




**3** Open the duplex cover.



**4** Remove the jammed paper.

**Note:** Make sure that all paper fragments are removed.




**5** Close the duplex cover and door B.


## Paper jam in the finisher bin

**1** Remove the jammed paper.


**Note:** Make sure that all paper fragments are removed.



**2** Open door C.




**3** Open door F.



**4** Remove the jammed paper.

**Note:** Make sure that all paper fragments are removed.




5 Close doors F and C.



**CAUTION—PINCH HAZARD:** To avoid the risk of a pinch injury, keep hands clear of the labeled area when closing door C.


## Staple jam in door G

1 Open door C.







**2** Open door G.



**3** Pull out the staple cartridge holder.



- 4 Lift the staple guard, and then remove the loose staples.




**Note:** Do not insert the staples that came out of the cartridge.

- 5 Close the staple guard.



- 6 Insert the staple cartridge holder.




- 7 Close doors G and C.



**CAUTION—PINCH HAZARD:** To avoid the risk of a pinch injury, keep hands clear of the labeled area when closing door C.

## Paper jam in door K


- 1 Open doors C and K.




- 2 Remove the jammed paper.

**Note:** Make sure that all paper fragments are removed.

- Using knob K1



- Using knob J2




### 3 Close doors K and C.



**CAUTION—PINCH HAZARD:** To avoid the risk of a pinch injury, keep hands clear of the labeled area when closing door C.

## Paper jam in door J


- 1 Open door J.




- 2 Remove the jammed paper.

**Note:** Make sure that all paper fragments are removed.

- Area J1



- Areas J3 and J4




- Areas J5 and J6



- 3 Close door J.


## Paper jam in door N

- 1 Open door N.



- 2 Remove the jammed paper.


**Note:** Make sure that all paper fragments are removed.



**3** Close door N.

## Paper jam in door L

**1** Open door L.



**2** Remove the jammed paper.


**Note:** Make sure that all paper fragments are removed.



3 Close door L.

## Paper jam in the staple finisher bin

1 Open door J.



2 Remove the jammed paper.

**Note:** Make sure that all paper fragments are removed.






**3** Close door J.

## Staple jam in door J


**1** Open door J.



**2** Remove the staple cartridge holder.




- 3** Open the staple guard, and then remove the loose staples.




**Note:** Do not insert the staples that came out of the cartridge.

- 4** Close the staple guard.



**5** Insert the staple cartridge holder.



**6** Close door J.

# Troubleshooting

## Network connection problems

### Cannot open Embedded Web Server

Action	Yes	No
<b>Step 1</b> Check if you are using a supported browser: <ul style="list-style-type: none"> <li>• Internet Explorer® version 9 or later</li> <li>• Safari version 8.0.3 or later</li> <li>• Google Chrome™</li> <li>• Mozilla Firefox</li> </ul> Is your browser supported?	Go to step 2.	Install a supported browser.
<b>Step 2</b> Make sure that the printer IP address is correct. View the printer IP address: <ul style="list-style-type: none"> <li>• From the home screen</li> <li>• From the TCP/IP section in the Network/Ports menu</li> <li>• By printing a network setup page or menu settings page, and then finding the TCP/IP section</li> </ul> <b>Note:</b> An IP address appears as four sets of numbers separated by periods, such as 123.123.123.123. Is the printer IP address correct?	Go to step 3.	Type the correct printer IP address in the address field.
<b>Step 3</b> Check if the printer is on. Is the printer on?	Go to step 4.	Turn on the printer.
<b>Step 4</b> Check if the network connection is working. Is the network connection working?	Go to step 5.	Contact your administrator.
<b>Step 5</b> Make sure that the cable connections to the printer and print server are secure. For more information, see the setup documentation that came with the printer. Are the cable connections secure?	Go to step 6.	Secure the cable connections.

Action	Yes	No
<b>Step 6</b> Check if the web proxy servers are disabled.  Are the web proxy servers disabled?	Go to step 7.	Contact your administrator.
<b>Step 7</b> Access the Embedded Web Server.  Did the Embedded Web Server open?	The problem is solved.	Contact <a href="#">customer support</a> .

## Unable to read flash drive

Action	Yes	No
<b>Step 1</b> Check if the flash drive is inserted into the front USB port. <b>Note:</b> The flash drive does not work when it is inserted into the rear USB port.  Is the flash drive inserted into the front USB port?	Go to step 2.	The problem is solved.
<b>Step 2</b> Check if the flash drive is supported. For more information, see <a href="#">“Supported flash drives and file types” on page 35</a>  Does the error message still appear?	Go to step 3.	The problem is solved.
<b>Step 3</b> Check if the front USB port is disabled. For more information, see <a href="#">“Enabling the USB port” on page 137</a> .  Does the error message still appear?	Contact <a href="#">customer support</a> .	The problem is solved.

## Enabling the USB port


From the home screen, touch **Settings > Network/Ports > USB > Enable USB Port**.

## Checking the printer connectivity

- 1 From the home screen, touch **Settings > Reports > Network > Network Setup Page**.
- 2 Check the first section of the network setup page, and confirm that the status is connected.  
 If the status is not connected, then the LAN drop may be inactive, or the network cable may be unplugged or malfunctioning. Contact your administrator for assistance.

## Hardware options problems

### Cannot detect internal option

Action	Yes	No
<b>Step 1</b> Turn off the printer, wait for about 10 seconds, and then turn it back on.  Does the internal option operate correctly?	The problem is solved.	Go to step 2.
<b>Step 2</b> Print a menu settings page, and then check if the internal option appears in the Installed Features list.  Is the internal option listed in the menu settings page?	Go to step 4.	Go to step 3.
<b>Step 3</b> Check if the internal option is properly installed in the controller board. <ul style="list-style-type: none"> <li><b>a</b> Turn off the printer, and then unplug the power cord from the electrical outlet.</li> <li><b>b</b> Make sure that the internal option is installed in the appropriate connector in the controller board.</li> <li><b>c</b> Connect the power cord to the electrical outlet, and then turn on the printer.</li> </ul>  <b>CAUTION—POTENTIAL INJURY:</b> To avoid the risk of fire or electrical shock, connect the power cord to an appropriately rated and properly grounded electrical outlet that is near the product and easily accessible.  Does the internal option operate correctly?	The problem is solved.	Go to step 4.
<b>Step 4</b> <ul style="list-style-type: none"> <li><b>a</b> Check if the internal option is available in the print driver.  <b>Note:</b> If necessary, manually add the internal option in the print driver to make it available for print jobs. For more information, see <a href="#">“Adding available options in the print driver” on page 200.</a></li> <li><b>b</b> Resend the print job.</li> </ul> Does the internal option operate correctly?	The problem is solved.	Contact <a href="#">customer support</a> .

## Internal solutions port does not operate correctly

Action	Yes	No
<b>Step 1</b> Print a menu settings page, and then check if the internal solutions port (ISP) appears in the Installed Features list.  Is the ISP listed in the Installed Features list?	Go to step 3.	Go to step 2.
<b>Step 2</b> Remove, and then install the ISP. For more information, see <a href="#">“Installing an internal solutions port” on page 179</a> . <b>Note:</b> Use a supported ISP.  Does the ISP operate correctly?	The problem is solved.	Go to step 3.
<b>Step 3</b> Check the cable and the ISP connection. <b>a</b> Use the correct cable, and then make sure that it is securely connected to the ISP. <b>b</b> Check if the ISP solution interface cable is securely connected into the receptacle of the controller board.  Does the ISP operate correctly?	The problem is solved.	Contact <a href="#">customer support</a> .

## Parallel or serial interface card does not operate correctly

Action	Yes	No
<b>Step 1</b> Print a menu settings page, and then check if the parallel or serial interface card appears in the Installed Features list.  Is the parallel or serial interface card listed in the Installed Features list?	Go to step 3.	Go to step 2.
<b>Step 2</b> Remove, and then install the parallel or serial interface card. For more information, see <a href="#">“Installing an internal solutions port” on page 179</a> .  Does the parallel or serial interface card operate correctly?	The problem is solved.	Go to step 3.
<b>Step 3</b> Check the connection between the cable and the parallel or serial interface card.  Does the parallel or serial interface card operate correctly?	The problem is solved.	Contact <a href="#">customer support</a> .

## Defective flash detected

Try one or more of the following:

- Replace the defective flash memory.
- From the printer control panel, select **Continue** to ignore the message and continue printing.
- Cancel the current print job.

## Not enough free space in flash memory for resources

Try one or more of the following:

- From the printer control panel, select **Continue** to clear the message and continue printing.
- Delete fonts, macros, and other data stored in the flash memory.
- Install flash memory with larger capacity.

**Note:** Downloaded fonts and macros that are not previously stored in the flash memory are deleted.

## Unformatted flash detected

Try one or more of the following:

- From the control panel, select **Continue** to stop the defragmentation and continue printing.
- Format the flash memory.

**Note:** If the error message remains, then the flash memory may be defective and needs to be replaced.

## Issues with supplies

### Replace cartridge, printer region mismatch

To correct this problem, purchase a cartridge with the correct region that matches the printer region, or purchase a worldwide cartridge.

- The first number in the message after 42 indicates the region of the printer.
- The second number in the message after 42 indicates the region of the cartridge.

#### Printer and toner cartridge regions

Region	Numeric code
Worldwide or Undefined region	0
North America (United States, Canada)	1
European Economic Area, Western Europe, Nordic countries, Switzerland	2
Asia Pacific	3
Latin America	4
Rest of Europe, Middle East, Africa	5
Australia, New Zealand	6



Region	Numeric code
Invalid region	9

**Note:** To find the region settings of the printer and toner cartridge, print the print quality test pages. From the control panel, navigate to: **Settings > Troubleshooting > Print Quality Test Pages**.

## Non-Lexmark supply

The printer has detected a non-Lexmark supply or part installed in the printer.

Your Lexmark printer is designed to function best with genuine Lexmark supplies and parts. Use of third-party supplies or parts may affect the performance, reliability, or life of the printer and its imaging components.

All life indicators are designed to function with Lexmark supplies and parts and may deliver unpredictable results if third-party supplies or parts are used. Imaging component usage beyond the intended life may damage your Lexmark printer or associated components.

**Warning—Potential Damage:** Use of third-party supplies or parts can affect warranty coverage. Damage caused by the use of third-party supplies or parts may not be covered by the warranty.

To accept any and all of these risks and to proceed with the use of non-genuine supplies or parts in your printer, from the control panel, press and hold **X** and **#** simultaneously for 15 seconds.

If you do not want to accept these risks, then remove the third-party supply or part from your printer and install a genuine Lexmark supply or part. For more information, see [“Using genuine Lexmark parts and supplies” on page 68](#).

If the printer does not print after pressing and holding **X** and **#** simultaneously for 15 seconds, then reset the supply usage counter.

- 1 From the control panel, navigate to:  
**Settings > Device > Maintenance > Configuration Menu > Supply Usage And Counters**
- 2 Select the part or supply that you want to reset, and then select **Start**.
- 3 Read the warning message, and then select **Continue**.
- 4 Press and hold **X** and **#** simultaneously for 15 seconds to clear the message.

**Note:** If you are unable to reset the supply usage counters, then return the item to the place of purchase.

## Scanner maintenance required, use ADF Kit

The printer is scheduled for maintenance. For more information, go to <http://support.lexmark.com> or contact your service representative, and then report the message.

## Paper feed problems

### Envelope seals when printing

Action	Yes	No
<p><b>1</b> Use envelopes that have been stored in a dry environment.</p> <p><b>Note:</b> Printing on envelopes with high moisture content can seal the flaps.</p> <p><b>2</b> Resend the print job.</p> <p>Does the envelope seal when printing?</p>	Contact <a href="#">customer support</a> .	The problem is solved.

### Collated printing does not work

Action	Yes	No
<p><b>Step 1</b></p> <p><b>a</b> From the home screen, touch <b>Settings &gt; Print &gt; Layout &gt; Collate</b>.</p> <p><b>b</b> Set Collate to On.</p> <p><b>c</b> Print the document.</p> <p>Are the pages collated correctly?</p>	The problem is solved.	Go to step 2.
<p><b>Step 2</b></p> <p><b>a</b> From the document that you are trying to print, open the Print dialog, and then select Collate.</p> <p><b>b</b> Print the document.</p> <p>Are the pages collated correctly?</p>	The problem is solved.	Go to step 3.
<p><b>Step 3</b></p> <p><b>a</b> Reduce the number of pages to print.</p> <p><b>b</b> Print the document.</p> <p>Are the pages collated correctly?</p>	The problem is solved.	Contact <a href="#">customer support</a> .

## Paper curl

Action	Yes	No
<b>Step 1</b> Move the paper guides in the tray to the correct position for the paper loaded.  Is the paper still curled?	Go to step 2.	The problem is solved.
<b>Step 2</b> <b>a</b> Depending on your operating system, specify the paper type and weight from the Printing Preferences or Print dialog.  <b>Notes:</b> <ul style="list-style-type: none"> <li>• Make sure that the settings match the paper loaded in the tray.</li> <li>• You can also change the settings on the printer control panel.</li> </ul> <b>b</b> Resend the print job.  Is the paper still curled?	Go to step 3.	The problem is solved.
<b>Step 3</b> <b>a</b> Remove paper from the tray, and then turn it over. <b>b</b> Resend the print job.  Is the paper still curled?	Go to step 4.	The problem is solved.
<b>Step 4</b> <b>a</b> Load paper from a fresh package. <b>Note:</b> Paper absorbs moisture due to high humidity. Store paper in its original wrapper until you are ready to use it. <b>b</b> Resend the print job.  Is the paper still curled?	Contact <a href="#">customer support</a> .	The problem is solved.

## Tray linking does not work

Action	Yes	No
<b>Step 1</b> <b>a</b> Check if the trays contain paper of the same size and type. <b>b</b> Check if the paper guides are positioned correctly. <b>c</b> Print the document.  Do the trays link correctly?	The problem is solved.	Go to step 2.

Action	Yes	No
<b>Step 2</b> <b>a</b> From the home screen, touch <b>Settings &gt; Paper &gt; Tray Configuration &gt; Paper Size/Type</b> . <b>b</b> Set the paper size and type to match the paper loaded in the linked trays. <b>c</b> Print the document.  Do the trays link correctly?	The problem is solved.	Contact <a href="#">customer support</a> .

## Check tray connection

Try one or more of the following:

- Turn off the printer, wait for about 10 seconds, and then turn it back on.

If the error occurs a second time, then:

- 1 Turn off the printer.
- 2 Unplug the power cord from the electrical outlet.
- 3 Remove the indicated tray.
- 4 Insert the tray.
- 5 Connect the power cord to the electrical outlet.



**CAUTION—POTENTIAL INJURY:** To avoid the risk of fire or electrical shock, connect the power cord to an appropriately rated and properly grounded electrical outlet that is near the product and easily accessible.

- 6 Turn on the printer.

If the error occurs again, then:

- 1 Turn off the printer.
  - 2 Unplug the power cord from the electrical outlet.
  - 3 Remove the indicated tray.
  - 4 Contact customer support.
- From the control panel, select **Continue** to clear the message and resume printing.

## Paper frequently jams

Action	Yes	No
<b>Step 1</b> <b>a</b> Pull out the tray. <b>b</b> Check if the paper is loaded correctly. <b>Notes:</b> <ul style="list-style-type: none"> <li>• Make sure that the paper guides are positioned correctly.</li> <li>• Make sure that the stack height is below the maximum paper fill indicator.</li> <li>• Make sure to print on recommended paper size and type.</li> </ul> <b>c</b> Insert the tray. <b>d</b> Print the document. Do paper jams still occur frequently?	Go to step 2.	The problem is solved.
<b>Step 2</b> <b>a</b> From the Paper menu on the control panel, check if the printer is detecting the correct paper size. <b>b</b> Resend the print job. Do paper jams still occur frequently?	Go to step 3.	The problem is solved.
<b>Step 3</b> <b>a</b> Load paper from a fresh package. <b>b</b> Print the document. Do paper jams still occur frequently?	Contact <a href="#">customer support</a> .	The problem is solved.

## Jammed pages are not reprinted

Action	Yes	No
<b>a</b> From the home screen, touch <b>Settings &gt; Device &gt; Notifications &gt; Jam Content Recovery</b> . <b>b</b> Select <b>On</b> or <b>Auto</b> . <b>c</b> Apply the changes. Are the jammed pages reprinted?	The problem is solved.	Contact <a href="#">customer support</a> .

## Printing problems

### Confidential and other held documents do not print

Action	Yes	No
<p><b>Step 1</b></p> <p><b>a</b> From the control panel, check if the documents appear in the Held Jobs list.</p> <p><b>Note:</b> If the documents are not listed, then print the documents using the Print and Hold options.</p> <p><b>b</b> Print the documents.</p> <p>Are the documents printed?</p>	The problem is solved.	Go to step 2.
<p><b>Step 2</b></p> <p>The print job may contain a formatting error or invalid data.</p> <ul style="list-style-type: none"> <li>• Delete the print job, and then send it again.</li> <li>• For PDF files, generate a new file, and then print the documents.</li> </ul> <p>Are the documents printed?</p>	The problem is solved.	Go to step 3.
<p><b>Step 3</b></p> <p>If you are printing from the Internet, then the printer may be reading the multiple job titles as duplicates.</p> <p><b>For Windows users</b></p> <p><b>a</b> Open the Printing Preferences dialog.</p> <p><b>b</b> From the Print and Hold section, select <b>Keep duplicate documents</b>.</p> <p><b>c</b> Enter a PIN.</p> <p><b>d</b> Resend the print job.</p> <p><b>For Macintosh users</b></p> <p><b>a</b> Save and name each job differently.</p> <p><b>b</b> Send the job individually.</p> <p>Are the documents printed?</p>	The problem is solved.	Go to step 4.
<p><b>Step 4</b></p> <p><b>a</b> Delete some held jobs to free up printer memory.</p> <p><b>b</b> Resend the print job.</p> <p>Are the documents printed?</p>	The problem is solved.	Go to step 5.

Action	Yes	No
<b>Step 5</b> <b>a</b> Add printer memory. <b>b</b> Resend the print job.  Are the documents printed?	The problem is solved.	Contact <a href="#">customer support</a> .

## Slow printing

Action	Yes	No
<b>Step 1</b> <b>a</b> Make sure that the printer is not in Eco-Mode and Quiet Mode. <b>b</b> Print the document.  Is the printer printing slow?	Go to step 2.	The problem is solved.
<b>Step 2</b> <b>a</b> Depending on your operating system, specify the paper type from the Printing Preferences or Print dialog.  <b>Notes:</b> <ul style="list-style-type: none"> <li>Make sure that the setting matches the paper loaded in the tray.</li> <li>You can also change the setting on the printer control panel.</li> </ul> <b>b</b> Print the document.  Is the printer printing slow?	Go to step 3.	The problem is solved.
<b>Step 3</b> <b>a</b> Reduce the number of pages to print. <b>b</b> Print the document.  Is the printer printing slow?	Go to step 4.	The problem is solved.
<b>Step 4</b> <b>a</b> Remove held jobs. <b>b</b> Print the document.  Is the printer printing slow?	Go to step 5.	The problem is solved.
<b>Step 5</b> <b>a</b> Connect the printer cable securely to the printer and the computer, print server, option, or other network device. <b>b</b> Print the document.  Is the printer printing slow?	Go to step 6.	The problem is solved.

Action	Yes	No
<b>Step 6</b> <b>a</b> From the Quality menu on the control panel, set the Print Resolution to 4800CQ. <b>b</b> Print the document.  Is the printer printing slow?	Go to step 7.	The problem is solved.
<b>Step 7</b> <b>a</b> Make sure that the printer is not overheating.  <b>Notes:</b> <ul style="list-style-type: none"> <li>• Allow the printer to cool down after a long print job.</li> <li>• Observe the recommended ambient temperature for the printer. For more information, see <a href="#">“Selecting a location for the printer” on page 11.</a></li> </ul> <b>b</b> Print the document.  Is the printer printing slow?	Go to step 8.	The problem is solved.
<b>Step 8</b> <b>a</b> Add more printer memory. <b>b</b> Print the document.  Is the printer printing slow?	Contact <a href="#">customer support</a> .	The problem is solved.

## Print jobs do not print


Action	Yes	No
<b>Step 1</b> <b>a</b> From the document you are trying to print, open the Print dialog, and then check if you have selected the correct printer. <b>b</b> Resend the print job.  Is the document printed?	The problem is solved.	Go to step 2.
<b>Step 2</b> <b>a</b> Check if the printer is on. <b>b</b> Resolve any error messages that appear on the display. <b>c</b> Resend the print job.  Is the document printed?	The problem is solved.	Go to step 3.



Action	Yes	No
<b>Step 3</b> <b>a</b> Check if the ports are working and if the cables are securely connected to the computer and the printer. For more information, see the setup documentation that came with the printer. <b>b</b> Resend the print job.  Is the document printed?	The problem is solved.	Go to step 4.
<b>Step 4</b> <b>a</b> Turn off the printer, wait for about 10 seconds, and then turn it back on. <b>b</b> Resend the print job.  Is the document printed?	The problem is solved.	Go to step 5.
<b>Step 5</b> <b>a</b> Remove, and then reinstall the printer software. <b>Note:</b> The printer software is available at <a href="http://support.lexmark.com">http://support.lexmark.com</a> . <b>b</b> Resend the print job.  Is the document printed?	The problem is solved.	Contact <a href="#">customer support</a> .

## Print quality is poor


### Blank or white pages



**Note:** Before solving the problem, print the quality sample pages to determine the missing color. From the home screen, touch **Settings** > **Troubleshooting** > **Basic Print Quality Pages**.

Action	Yes	No
<b>Step 1</b> <b>a</b> Remove, and then reinstall the imaging unit or imaging kit. <b>Warning—Potential Damage:</b> Do not expose the imaging unit or imaging kit to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems. <b>Warning—Potential Damage:</b> To avoid damage, do not touch the underside of the imaging unit or imaging kit. <b>b</b> Print a document.  Is the printer still printing blank or white pages?	Go to step 2.	The problem is solved.
<b>Step 2</b> <b>a</b> Replace the imaging unit or imaging kit. <b>Warning—Potential Damage:</b> Do not expose the imaging unit or imaging kit to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems. <b>Warning—Potential Damage:</b> To avoid damage, do not touch the underside of the imaging unit or imaging kit. <b>b</b> Print a document.  Is the printer still printing blank or white pages?	Contact <a href="#">customer support</a> .	The problem is solved.


## Dark print



Action	Yes	No
<b>Step 1</b> <b>a</b> From the Quality menu on the control panel, select <b>Color Adjust</b> . <b>b</b> Resend the print job.  Is the print still too dark?	Go to step 2.	The problem is solved.


Action	Yes	No
<b>Step 2</b> <b>a</b> Depending on your operating system, reduce the toner darkness from the Printing Preferences or Print dialog. <b>Note:</b> You can also change the settings on the printer control panel. <b>b</b> Resend the print job.  Is the print still too dark?	Go to step 3.	The problem is solved.
<b>Step 3</b> <b>a</b> Depending on your operating system, specify the paper type, texture, and weight from the Printing Preferences or Print dialog. <b>Notes:</b> <ul style="list-style-type: none"> <li>• Make sure that the settings match the paper loaded in the tray.</li> <li>• You can also change the settings on the printer control panel.</li> </ul> <b>b</b> Resend the print job.  Is the print still too dark?	Go to step 4.	The problem is solved.
<b>Step 4</b> Make sure that the paper has no texture or rough finishes.  Are you printing on textured or rough paper?	Change the texture settings to match the paper you are printing on.	Go to step 5.
<b>Step 5</b> <b>a</b> Load paper from a fresh package. <b>Note:</b> Paper absorbs moisture due to high humidity. Store paper in its original wrapper until you are ready to use it. <b>b</b> Resend the print job.  Is the print still too dark?	Go to step 6.	The problem is solved.
<b>Step 6</b> Replace the imaging unit or imaging kit, and then resend the print job.  Is the print still too dark?	Contact <a href="#">customer support</a> .	The problem is solved.

## Ghost images




Action	Yes	No
<b>Step 1</b> <b>a</b> Load the tray with the correct paper type and weight. <b>b</b> Resend the print job.  Do ghost images still appear on prints?	Go to step 2.	The problem is solved.
<b>Step 2</b> <b>a</b> Depending on your operating system, specify the paper type and weight from the Printing Preferences or Print dialog.  <b>Notes:</b> <ul style="list-style-type: none"> <li>Make sure that the settings match the paper loaded in the tray.</li> <li>You can also change the settings on the printer control panel.</li> </ul> <b>b</b> Resend the print job.  Do ghost images still appear on prints?	Go to step 3.	The problem is solved.
<b>Step 3</b> <b>a</b> From the Quality menu on the control panel, select <b>Color Adjust</b> . <b>b</b> Resend the print job.  Do ghost images still appear on prints?	Contact <a href="#">customer support</a> .	The problem is solved.

## Gray background



Action	Yes	No
<b>Step 1</b> <b>a</b> From the home screen, touch <b>Settings &gt; Print &gt; Quality</b> . <b>b</b> Adjust the toner darkness. <b>c</b> Print the document.  Does gray background still appear on prints?	Go to step 2.	The problem is solved.
<b>Step 2</b> <b>a</b> From the home screen, touch <b>Settings &gt; Print &gt; Quality &gt; Advanced Imaging &gt; Color Adjust</b> . <b>b</b> Start the process. <b>c</b> Print the document.  Does gray background still appear on prints?	Go to step 3.	The problem is solved.
<b>Step 3</b> <b>a</b> Remove, and then reinstall the imaging unit or imaging kit. <b>Warning—Potential Damage:</b> Do not expose the imaging unit or imaging kit to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems. <b>Warning—Potential Damage:</b> To avoid damage, do not touch the underside of the imaging unit or imaging kit. <b>b</b> Print the document.  Does gray background still appear on prints?	Contact <a href="#">customer support</a> .	The problem is solved.

## Horizontal dark lines




**Note:** If horizontal dark lines keep appearing on your prints, then see the “Repeating defects” topic.

Action	Yes	No
<b>Step 1</b> <b>a</b> Depending on your operating system, specify the tray or feeder from the Printing Preferences or Print dialog. <b>b</b> Resend the print job.  Do horizontal dark lines still appear on prints?	Go to step 2.	The problem is solved.

Action	Yes	No
<b>Step 2</b> <b>a</b> Depending on your operating system, specify the paper type and weight from the Printing Preferences or from Print dialog. <b>Notes:</b> <ul style="list-style-type: none"> <li>Make sure that the settings match the paper loaded in the tray.</li> <li>You can also change the settings on the printer control panel.</li> </ul> <b>b</b> Resend the print job. Do horizontal dark lines still appear on prints?	Go to step 3.	The problem is solved.
<b>Step 3</b> <b>a</b> Load paper from a fresh package. <b>Note:</b> Paper absorbs moisture due to high humidity. Store paper in its original wrapper until you use it. <b>b</b> Resend the print job. Do horizontal dark lines still appear on prints?	Go to step 4.	The problem is solved.
<b>Step 4</b> <b>a</b> Remove, and then reinstall the imaging unit or imaging kit. <b>Warning—Potential Damage:</b> Do not expose the imaging unit or imaging kit to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems. <b>Warning—Potential Damage:</b> To avoid damage, do not touch the underside of the imaging unit or imaging kit. <b>b</b> Resend the print job. Do horizontal dark lines still appear on prints?	Go to step 5.	The problem is solved.
<b>Step 5</b> Replace the imaging unit or imaging kit, and then resend the print job. Do horizontal dark lines still appear on prints?	Contact <a href="#">customer support</a> .	The problem is solved.


## Horizontal white lines



**Note:** If horizontal dark lines keep appearing on your prints, then see the “Repeating defects” topic.


Action	Yes	No
<b>Step 1</b> <b>a</b> Depending on your operating system, specify the paper type and weight from the Printing Preferences or Print dialog. <b>Notes:</b> <ul style="list-style-type: none"> <li>• Make sure that the settings match the paper loaded in the tray.</li> <li>• You can also change the settings on the printer control panel.</li> </ul> <b>b</b> Resend the print job. Do horizontal white lines still appear on prints?	Go to step 2.	The problem is solved.
<b>Step 2</b> <b>a</b> Load the specified tray or feeder with the recommended paper type. <b>b</b> Resend the print job. Do horizontal white lines still appear on prints?	Go to step 3.	The problem is solved.
<b>Step 3</b> <b>a</b> Remove, and then reinstall the imaging unit or imaging kit. <b>Warning—Potential Damage:</b> Do not expose the imaging unit or imaging kit to direct light for more than 10 minutes. Extended exposure to light can cause print quality problems. <b>Warning—Potential Damage:</b> To avoid damage, do not touch the underside of the imaging unit or imaging kit. <b>b</b> Resend the print job. Do horizontal white lines still appear on prints?	Go to step 4.	The problem is solved.
<b>Step 4</b> Replace the imaging unit or imaging kit, and then resend the print job. Do horizontal white lines still appear on prints?	Contact <a href="#">customer support</a> .	The problem is solved.

## Incorrect margins



Action	Yes	No
<b>Step 1</b> <b>a</b> Squeeze and slide the paper guides to the correct position for the size of the paper you are loading. <b>b</b> Resend the print job.  Are the margins correct?	The problem is solved.	Go to step 2.
<b>Step 2</b> <b>a</b> From the Paper menu on the control panel, check if the printer is detecting the correct paper size. <b>b</b> Resend the print job.  Are the margins correct?	The problem is solved.	Go to step 3.
<b>Step 3</b> <b>a</b> Depending on your operating system, specify the paper size from the Printing Preferences or Print dialog.  <b>Notes:</b> <ul style="list-style-type: none"> <li>• Make sure that the settings match the paper loaded in the tray.</li> <li>• You can also change the settings on the printer control panel.</li> </ul> <b>b</b> Resend the print job.  Are the margins correct?	The problem is solved.	Contact <a href="#">customer support</a> .


### Jagged or uneven characters





Action	Yes	No
<p><b>a</b> Check if the printer supports the fonts that are installed on your computer.</p> <p><b>1</b> From the control panel, touch:</p> <p><b>Settings &gt; Reports &gt; Print &gt; Print Fonts</b></p> <p><b>2</b> Select <b>PCL Fonts</b> or <b>PS Fonts</b>.</p> <p><b>b</b> If the font is not supported, then install a supported font. For more information, contact your administrator.</p> <p><b>c</b> Resend the print job.</p> <p>Do prints still contain jagged or uneven characters?</p>	Contact <a href="#">customer support</a> .	The problem is solved.


## Light print



Action	Yes	No
<p><b>Step 1</b></p> <p><b>a</b> From the Quality menu on the control panel, select <b>Color Adjust</b>.</p> <p><b>b</b> Resend the print job.</p> <p>Is the print still too light?</p>	Go to step 2.	The problem is solved.
<p><b>Step 2</b></p> <p><b>a</b> Depending on your operating system, increase the toner darkness from the Printing Preferences or Print dialog.</p> <p><b>Note:</b> You can also change the settings on the printer control panel.</p> <p><b>b</b> Resend the print job.</p> <p>Is the print still too light?</p>	Go to step 3.	The problem is solved.


Action	Yes	No
<b>Step 3</b> <b>a</b> Depending on your operating system, specify the paper type, texture, and weight from the Printing Preferences or Print dialog.  <b>Notes:</b> <ul style="list-style-type: none"> <li>• Make sure that the settings match the paper loaded in the tray.</li> <li>• You can also change the settings on the printer control panel.</li> </ul> <b>b</b> Resend the print job.  Is the print still too light?	Go to step 4.	The problem is solved.
<b>Step 4</b> Make sure that the paper has no texture or rough finishes.  Are you printing on textured or rough paper?	Change the texture settings to match the paper you are printing on.	Go to step 5.
<b>Step 5</b> <b>a</b> Load paper from a fresh package. <b>Note:</b> Paper absorbs moisture due to high humidity. Store paper in its original wrapper until you are ready to use it. <b>b</b> Resend the print job.  Is the print still too light?	Go to step 6.	The problem is solved.
<b>Step 6</b> Replace the imaging unit or imaging kit, and then resend the print job.  <b>Warning—Potential Damage:</b> Do not expose the imaging unit or imaging kit to direct light for more than 10 minutes. Extended exposure to light can cause print quality problems.  <b>Warning—Potential Damage:</b> To avoid damage, do not touch the underside of the imaging unit or imaging kit.  Is the print still too light?	Contact <a href="#">customer support</a> .	The problem is solved.

## Mottled print and dots




Action	Yes	No
<b>Step 1</b> Check the printer for leaked toner contamination.  Is the printer free of leaked toner?	Go to step 2.	Contact <a href="#">customer support</a> .
<b>Step 2</b> <b>a</b> From the home screen, touch <b>Settings &gt; Device &gt; Preferences</b> . <b>b</b> Check if the paper type and size settings match the paper type and size set in the tray.  Do the settings match?	Go to step 4.	Go to step 3.
<b>Step 3</b> <b>a</b> Change the paper size and type in the Paper menu or adjust the size settings in the tray. <b>b</b> Print the document.  Is the print still mottled?	Go to step 4.	The problem is solved.
<b>Step 4</b> <b>a</b> Replace the textured or rough paper loaded in the tray with plain paper. <b>b</b> Print the document.  Is the print still mottled?	Go to step 5.	The problem is solved.
<b>Step 5</b> <b>a</b> Replace the imaging unit or imaging kit. <b>Warning—Potential Damage:</b> Do not expose the imaging unit or imaging kit to direct light for more than 10 minutes. Extended exposure to light can cause print quality problems. <b>Warning—Potential Damage:</b> To avoid damage, do not touch the underside of the imaging unit or imaging kit. <b>b</b> Print the document.  Is the print still mottled?	Contact <a href="#">customer support</a> .	The problem is solved.

## Print crooked or skewed



Action	Yes	No
<b>Step 1</b> <b>a</b> Remove the tray. <b>b</b> Remove the paper, and then load paper from a fresh package. <b>Note:</b> Paper absorbs moisture due to high humidity. Store paper in its original wrapper until you are ready to use it. <b>c</b> Squeeze and slide the paper guides to the correct position for the size of the paper you are loading. <b>d</b> Insert the tray. <b>e</b> Resend the print job.  Is the print still crooked or skewed?	Go to step 2.	The problem is solved.
<b>Step 2</b> <b>a</b> Check if you are printing on a supported paper. <b>b</b> Resend the print job.  Is the print still crooked or skewed?	Contact <a href="#">customer support</a> .	The problem is solved.

## Repeating defects



**Note:** Before solving the problem, print the *Maintenance Defect Ruler* from the Troubleshooting section of the Settings menu.

Action	Yes	No
<b>Step 1</b> <b>a</b> Print the quality sample pages. From the home screen, touch <b>Settings &gt; Troubleshooting &gt; Basic Print Quality Samples</b> . <b>b</b> Determine how many colors have defects.  Is only one color affected?	Go to step 2.	Go to step 3.


Action	Yes	No
<p><b>Step 2</b></p> <p><b>a</b> Using the <i>Maintenance Defect Ruler</i>, measure the distance between the repeating defects on the affected color page.</p> <p><b>b</b> Replace the supply item that matches the measurement on the affected color page.</p> <p><b>Photoconductor unit</b></p> <ul style="list-style-type: none"> <li>• 125.70 mm (4.95 in.)</li> <li>• 35.40 mm (1.39 in.)</li> </ul> <p><b>Developer unit</b></p> <p>42 mm (1.65 in.)</p> <p><b>c</b> Print the quality sample pages.</p> <p>Do the defects still appear?</p>	<p>Take note of the distance, and then contact <a href="#">customer support</a> or your service representative.</p>	<p>The problem is solved.</p>
<p><b>Step 3</b></p> <p><b>a</b> Using the <i>Maintenance Defect Ruler</i>, measure the distance between the repeating defects on the affected color page.</p> <p><b>b</b> Replace the supply item that matches the measurement on the affected color page.</p> <p><b>Transfer roller</b></p> <p>78.50 mm (3.09 in.)</p> <p><b>Transfer module</b></p> <ul style="list-style-type: none"> <li>• 47.10 mm (1.86 in.)</li> <li>• 90 mm (3.54 in.)</li> </ul> <p><b>Fuser</b></p> <ul style="list-style-type: none"> <li>• 96.60 mm (3.80 in.)</li> <li>• 127.60 mm (5.02 in.)</li> </ul> <p><b>c</b> Print the quality sample pages.</p> <p>Do the defects still appear?</p>	<p>Take note of the distance, and then contact <a href="#">customer support</a> or your service representative.</p>	<p>The problem is solved.</p>

## Solid color or black images



Action	Yes	No
<b>Step 1</b> <b>a</b> Remove, and then reinstall the imaging unit or imaging kit. <b>Warning—Potential Damage:</b> Do not expose the imaging unit or imaging kit to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems. <b>Warning—Potential Damage:</b> To avoid damage, do not touch the underside of the imaging unit or imaging kit. <b>b</b> Resend the print job.  Is the printer still printing solid color or black images?	Go to step 2.	The problem is solved.
<b>Step 2</b> Replace the imaging unit or imaging kit, and then resend the print job.  Is the printer still printing solid color or black images?	Contact <a href="#">customer support</a> .	The problem is solved.


### Text or images cut off



Action	Yes	No
<b>Step 1</b> <b>a</b> Move the paper guides in the tray to the correct position for the paper loaded. <b>b</b> Resend the print job.  Is the page or image still clipped?	Go to step 2.	The problem is solved.
<b>Step 2</b> <b>a</b> Depending on your operating system, specify the paper size from the Printing Preferences or Print dialog. <b>Notes:</b> <ul style="list-style-type: none"> <li>Make sure that the settings match the paper loaded in the tray.</li> <li>You can also change the settings on the printer control panel.</li> </ul> <b>b</b> Resend the print job.  Is the page or image still clipped?	Go to step 3.	The problem is solved.


Action	Yes	No
<b>Step 3</b> <b>a</b> Remove, and then reinstall the imaging unit or imaging kit. <b>Warning—Potential Damage:</b> Do not expose the imaging unit or imaging kit to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems. <b>Warning—Potential Damage:</b> To avoid damage, do not touch the underside of the imaging unit or imaging kit. <b>b</b> Resend the print job.  Is the page or image still clipped?	Contact <a href="#">customer support</a> .	The problem is solved.

## Toner easily rubs off





Action	Yes	No
<b>1</b> Depending on your operating system, specify the paper type, texture, and weight from the Printing Preferences or Print dialog.  <b>Notes:</b> <ul style="list-style-type: none"> <li>• Make sure that the settings match the paper loaded in the tray.</li> <li>• You can also change the settings on the printer control panel.</li> </ul> <b>2</b> Resend the print job.  Does the toner still rub off?	Contact <a href="#">customer support</a> .	The problem is solved.

## Uneven print density



Action	Yes	No
<p>Replace the imaging unit or imaging kit, and then resend the print job.</p> <p><b>Warning—Potential Damage:</b> Do not expose the imaging unit or imaging kit to direct light for more than 10 minutes. Extended exposure to light can cause print quality problems.</p> <p><b>Warning—Potential Damage:</b> To avoid damage, do not touch the underside of the imaging unit or imaging kit.</p> <p>Is the print density uneven?</p>	Contact <a href="#">customer support</a> .	The problem is solved.

## Vertical dark lines or streaks



Action	Yes	No
<p><b>Step 1</b></p> <p><b>a</b> Depending on your operating system, specify the paper type, texture, and weight from the Printing Preferences or Print dialog.</p> <p><b>Notes:</b></p> <ul style="list-style-type: none"> <li>Make sure that the settings match the paper loaded in the tray.</li> <li>You can also change the settings on the printer control panel.</li> </ul> <p><b>b</b> Resend the print job.</p> <p>Do vertical dark lines or streaks still appear on prints?</p>	Go to step 2.	The problem is solved.
<p><b>Step 2</b></p> <p><b>a</b> Load paper from a fresh package.</p> <p><b>Note:</b> Paper absorbs moisture due to high humidity. Store paper in its original wrapper until you use it.</p> <p><b>b</b> Resend the print job.</p> <p>Do vertical dark lines or streaks still appear on prints?</p>	Go to step 3.	The problem is solved.



Action	Yes	No
<b>Step 3</b> <b>a</b> Remove, and then reinstall the imaging unit or imaging kit. <b>Warning—Potential Damage:</b> Do not expose the imaging unit or imaging kit to direct light for more than 10 minutes. Extended exposure to light can cause print quality problems. <b>Warning—Potential Damage:</b> To avoid damage, do not touch the underside of the imaging unit or imaging kit. <b>b</b> Resend the print job.  Do vertical dark lines or streaks still appear on prints?	Go to step 4.	The problem is solved.
<b>Step 4</b> Replace the imaging unit or imaging kit, and then resend the print job.  Do vertical dark lines or streaks still appear on prints?	Contact <a href="#">customer support</a> .	The problem is solved.


## Vertical white lines



Action	Yes	No
<b>Step 1</b> <b>a</b> Depending on your operating system, specify the paper type and weight from the Printing Preferences or Print dialog. <b>Notes:</b> <ul style="list-style-type: none"> <li>Make sure that the settings match the paper loaded in the tray.</li> <li>You can also change the settings on the printer control panel.</li> </ul> <b>b</b> Resend the print job.  Do vertical white lines still appear on prints?	Go to step 2.	The problem is solved.

Action	Yes	No
<b>Step 2</b> Check if you are using the recommended paper type. <b>a</b> Load the specified tray or feeder with the recommended paper type. <b>b</b> Resend the print job.  Do vertical white lines still appear on prints?	Go to step 3.	The problem is solved.
<b>Step 3</b> <b>a</b> Remove, and then reinstall the imaging unit or imaging kit. <b>Warning—Potential Damage:</b> Do not expose the imaging unit or imaging kit to direct light for more than 10 minutes. Extended exposure to light may cause print quality problems. <b>Warning—Potential Damage:</b> To avoid damage, do not touch the underside of the imaging unit or imaging kit. <b>b</b> Resend the print job.  Do vertical white lines still appear on prints?	Go to step 4.	The problem is solved.
<b>Step 4</b> Replace the imaging unit or imaging kit, and then resend the print job.  Do vertical white lines still appear on prints?	Contact <a href="#">customer support</a> .	The problem is solved.

## The printer is not responding

Action	Yes	No
<b>Step 1</b> Connect the power cord to the electrical outlet.  <b>CAUTION—POTENTIAL INJURY:</b> To avoid the risk of fire or electrical shock, connect the power cord to an appropriately rated and properly grounded electrical outlet that is near the product and easily accessible.  Is the printer responding?	The problem is solved.	Go to step 2.
<b>Step 2</b> Check if the electrical outlet is turned off by a switch or breaker.  Is the electrical outlet turned off by a switch or breaker?	Turn on the switch or reset the breaker.	Go to step 3.
<b>Step 3</b> Check if the printer is on.  Is the printer on?	Go to step 4.	Turn on the printer.

Action	Yes	No
<b>Step 4</b> Check if the printer is in sleep or hibernate mode.  Is the printer in sleep or hibernate mode?	Press the power button to wake the printer.	Go to step 5.
<b>Step 5</b> Check if the cables connecting the printer and the computer are inserted in the correct ports.  Are the cables inserted in the correct ports?	Go to step 6.	Make sure to match the following: <ul style="list-style-type: none"> <li>• The USB cable with the USB port on the printer</li> <li>• The Ethernet cable with the Ethernet port on the printer</li> </ul>
<b>Step 6</b> Turn off the printer, reinstall the hardware options, and then turn it back on. For more information, see the documentation that came with the option.  Is the printer responding?	The problem is solved	Go to step 7.
<b>Step 7</b> Install the correct print driver.  Is the printer responding?	The problem is solved	Go to step 8.
<b>Step 8</b> Turn off the printer, wait for about 10 seconds, and then turn it back on.  Is the printer responding?	The problem is solved.	Contact <a href="#">customer support</a> .

## Job prints from the wrong tray or on the wrong paper

Action	Yes	No
<b>Step 1</b> <b>a</b> Check if you are printing on a supported paper. <b>b</b> Print the document.  Is the document printed from the correct tray or on the correct paper?	The problem is solved.	Go to step 2.

Action	Yes	No
<p><b>Step 2</b></p> <p><b>a</b> Depending on your operating system, specify the paper size from the Printing Preferences or Print dialog.</p> <p><b>Notes:</b></p> <ul style="list-style-type: none"> <li>• Make sure that the settings match the paper loaded in the tray.</li> <li>• You can also change the settings on the printer control panel.</li> </ul> <p><b>b</b> Print the document.</p> <p>Is the document printed from the correct tray or on the correct paper?</p>	The problem is solved.	Go to step 3.
<p><b>Step 3</b></p> <p><b>a</b> Check if the trays are not linked.</p> <p><b>b</b> Print the document.</p> <p>Is the document printed from the correct tray or on the correct paper?</p>	The problem is solved.	Contact <a href="#">customer support</a> .

## Color quality problems

### Adjusting toner darkness

- 1 From the home screen, touch **Settings > Print > Quality**.
- 2 Adjust the toner darkness.
- 3 Apply the changes.

### Modifying the colors in printed output

- 1 From the home screen, touch **Settings > Print > Quality > Advanced Imaging > Color Correction > Manual**.
- 2 From the Advanced Imaging menu, select **Color Correction Content**.
- 3 Choose the appropriate color conversion setting.

Object type	Color conversion tables
RGB Image RGB Text RGB Graphics	<ul style="list-style-type: none"> <li>• <b>Vivid</b>—Produces brighter, more saturated colors and may be applied to all incoming color formats.</li> <li>• <b>sRGB Display</b>—Produces an output that approximates the colors displayed on a computer monitor. Black toner usage is optimized for printing photographs.</li> <li>• <b>Display-True Black</b>—Produces an output that approximates the colors displayed on a computer monitor. This setting uses only black toner to create all levels of neutral gray.</li> <li>• <b>sRGB Vivid</b>—Provides an increased color saturation for the sRGB Display color correction. Black toner usage is optimized for printing business graphics.</li> <li>• <b>Off</b></li> </ul>
CMYK Image CMYK Text CMYK Graphics	<ul style="list-style-type: none"> <li>• <b>US CMYK</b>—Applies color correction to approximate the Specifications for Web Offset Publishing (SWOP) color output.</li> <li>• <b>Euro CMYK</b>—Applies color correction to approximate Euroscale color output.</li> <li>• <b>Vivid CMYK</b>—Increases the color saturation of the US CMYK color correction setting.</li> <li>• <b>Off</b></li> </ul>

## FAQ about color printing

### What is RGB color?

RGB color is a method of describing colors by indicating the amount of red, green, or blue used to produce a certain color. Red, green, and blue light can be added in various amounts to produce a large range of colors observed in nature. Computer screens, scanners, and digital cameras use this method to display colors.

### What is CMYK color?

CMYK color is a method of describing colors by indicating the amount of cyan, magenta, yellow, and black used to reproduce a particular color. Cyan, magenta, yellow, and black inks or toners can be printed in various amounts to produce a large range of colors observed in nature. Printing presses, inkjet printers, and color laser printers create colors in this manner.

### How is color specified in a document to be printed?

Software programs are used to specify and modify the document color using RGB or CMYK color combinations. For more information, see the software program Help topics.

### How does the printer know what color to print?

When printing a document, information describing the type and color of each object is sent to the printer and is passed through color conversion tables. Color is translated into the appropriate amounts of cyan, magenta, yellow, and black toner used to produce the color you want. The object information determines the application of color conversion tables. For example, it is possible to apply one type of color conversion table to text while applying a different color conversion table to photographic images.

### What is manual color correction?

When manual color correction is enabled, the printer employs user-selected color conversion tables to process objects. Manual color correction settings are specific to the type of object being printed (text, graphics, or images). It is also specific to how the color of the object is specified in the software program (RGB or CMYK combinations). To apply a different color conversion table manually, see [“Modifying the colors in printed output” on page 168](#).

If the software program does not specify colors with RGB or CMYK combinations, then manual color correction is not useful. It is also not effective if the software program or the computer operating system controls the adjustment of colors. In most situations, setting the Color Correction to Auto generates preferred colors for the documents.

### How can I match a particular color (such as a corporate logo)?

From the printer Quality menu, nine types of Color Samples sets are available. These sets are also available from the Color Samples page of the Embedded Web Server. Selecting any sample set generates multiple-page prints consisting of hundreds of colored boxes. Each box contains a CMYK or RGB combination, depending on the table selected. The observed color of each box is obtained by passing the CMYK or RGB combination labeled on the box through the selected color conversion table.

By examining Color Samples sets, you can identify the box with color closest to the color being matched. The color combination labeled on the box can then be used for modifying the color of the object in a software program. For more information, see the software program Help topics. Manual color correction may be necessary to use the selected color conversion table for the particular object.

Selecting which Color Samples set to use for a particular color-matching problem depends on:

- The Color Correction setting being used (Auto, Off, or Manual)
- The type of object being printed (text, graphics, or images)
- How the color of the object is specified in the software program (RGB or CMYK combinations)

If the software program does not specify colors with RGB or CMYK combinations, then the Color Samples pages are not useful. Additionally, some software programs adjust the RGB or CMYK combinations specified in the program through color management. In these situations, the printed color may not be an exact match of the Color Samples pages.

### The print appears tinted

Action	No	Yes
<p>Adjust the color balance.</p> <p><b>a</b> From the home screen, touch <b>Settings &gt; Print &gt; Quality &gt; Advanced Imaging &gt; Color Balance</b>.</p> <p><b>b</b> Adjust the setting.</p> <p><b>c</b> Resend the print job.</p> <p>Does the print still appear tinted?</p>	<p>The problem is solved.</p>	<p>Contact <a href="#">customer support</a>.</p>

## Faxing problems

### Cannot send or receive faxes

Action	Yes	No
<b>Step 1</b> Resolve any error messages that appear on the display.  Can you send or receive a fax?	The problem is solved.	Go to step 2.
<b>Step 2</b> Make sure that the cable connections for the following equipment are secure: <ul style="list-style-type: none"> <li>• Telephone</li> <li>• Handset</li> <li>• Answering machine</li> </ul> Can you send or receive a fax?	The problem is solved.	Go to step 3.
<b>Step 3</b> Check for a dial tone. <ul style="list-style-type: none"> <li>• Call the fax number to check if it is working properly.</li> <li>• If you are using the On Hook Dial feature, then turn up the volume to check if you hear a dial tone.</li> </ul> Can you hear a dial tone?	Go to step 5.	Go to step 4.
<b>Step 4</b> Check the telephone wall jack. <ul style="list-style-type: none"> <li><b>a</b> Connect the analog telephone directly to the wall jack.</li> <li><b>b</b> Listen for a dial tone.</li> <li><b>c</b> If you do not hear a dial tone, then use a different telephone cable.</li> <li><b>d</b> If you still do not hear a dial tone, then connect the analog telephone to a different wall jack.</li> <li><b>e</b> If you hear a dial tone, then connect the printer to that wall jack.</li> </ul> Can you send or receive a fax?	The problem is solved.	Go to step 5.

Action	Yes	No
<p><b>Step 5</b></p> <p>Check if the printer is connected to an analog phone service or to the correct digital connector.</p> <ul style="list-style-type: none"> <li>• If you are using an Integrated Services for Digital Network (ISDN) telephone service, then connect to an analog telephone port of an ISDN terminal adapter. For more information, contact your ISDN provider.</li> <li>• If you are using DSL, then connect to a DSL filter or router that supports analog use. For more information, contact your DSL provider.</li> <li>• If you are using a private branch exchange (PBX) telephone service, then make sure that you are connecting to an analog connection on the PBX. If none exists, then consider installing an analog telephone line for the fax machine.</li> </ul> <p>Can you send or receive a fax?</p>	The problem is solved.	Go to step 6.
<p><b>Step 6</b></p> <p>Temporarily disconnect other equipment and disable other telephone services.</p> <ul style="list-style-type: none"> <li><b>a</b> Disconnect other equipment (such as answering machines, computers, modems, or telephone line splitters) between the printer and the telephone line.</li> <li><b>b</b> Disable call waiting and voice mail. For more information, contact your telephone company.</li> </ul> <p>Can you send or receive a fax?</p>	The problem is solved.	Go to step 7.
<p><b>Step 7</b></p> <p>Scan the original document one page at a time.</p> <ul style="list-style-type: none"> <li><b>a</b> Dial the fax number.</li> <li><b>b</b> Scan the document.</li> </ul> <p>Can you send or receive a fax?</p>	The problem is solved.	Contact <a href="#">customer support</a> .



## Can receive but not send faxes

Action	Yes	No
<b>Step 1</b> Load the original document properly into the ADF tray or on the scanner glass.  Can you send faxes?	The problem is solved.	Go to step 2.
<b>Step 2</b> Set up the shortcut number properly. <ul style="list-style-type: none"> <li>• Check if the shortcut number is set for the telephone number that you want to dial.</li> <li>• Dial the telephone number manually.</li> </ul> Can you send faxes?	The problem is solved.	Contact <a href="#">customer support</a> .

## Can send but not receive faxes

Action	Yes	No
<b>Step 1</b> Make sure that the tray or multipurpose feeder is not empty.  Can you receive faxes?	The problem is solved.	Go to step 2.
<b>Step 2</b> Check the ring count delay settings. <ul style="list-style-type: none"> <li><b>a</b> From the home screen, touch <b>Settings &gt; Fax &gt; Analog Fax Setup &gt; Fax Receive Settings &gt; Rings to Answer</b>.</li> <li><b>b</b> If necessary, configure the setting.</li> </ul> Can you receive faxes?	The problem is solved.	Go to step 3.
<b>Step 3</b> Replace the toner cartridge. For more information, see the instruction sheet that came with the supply.  Can you receive faxes?	The problem is solved.	Contact <a href="#">customer support</a> .

## Poor fax print quality

Action	Yes	No
<b>Step 1</b> Enhance the print quality. <b>a</b> From the home screen, touch <b>Settings &gt; Print &gt; Quality</b> . <b>b</b> Adjust the settings.  Is the fax print quality satisfactory?	The problem is solved.	Go to step 2.
<b>Step 2</b> Decrease the incoming fax transmission speed. <b>a</b> From the home screen, touch <b>Settings &gt; Fax &gt; Analog Fax Setup &gt; Fax Receive Settings &gt; Admin Controls &gt; Max Speed</b> . <b>b</b> Select a lower transmission speed.  Is the fax print quality satisfactory?	The problem is solved.	Go to step 3.
<b>Step 3</b> Replace the toner cartridge. For more information, see the instruction sheet that came with the supply.  Is the fax print quality satisfactory?	The problem is solved.	Contact <a href="#">customer support</a> .

## Scanning problems

### Cannot scan from a computer

Action	Yes	No
<b>Step 1</b> <b>a</b> Turn off the printer, wait for about 10 seconds, and then turn it back on. <b>b</b> Resend the scan job.  Can you send the scan job?	The problem is solved.	Go to step 2.
<b>Step 2</b> <b>a</b> Make sure that the cables between the printer and the print server are secure. For more information, see the setup documentation that came with the printer. <b>b</b> Resend the scan job.  Can you send the scan job?	The problem is solved.	Contact <a href="#">customer support</a> .

## Partial copies of document or photo

Action	Yes	No
<b>Step 1</b> <b>a</b> Make sure that the document or photo is loaded facedown on the upper left corner of the scanner glass. <b>b</b> Copy the document or photo.  Is the document or photo copied correctly?	The problem is solved.	Go to step 2.
<b>Step 2</b> <b>a</b> Match the paper size setting and the paper loaded in the tray. <b>b</b> Copy the document or photo.  Is the document or photo copied correctly?	The problem is solved.	Contact <a href="#">customer support</a> .

## Poor copy quality

Action	Yes	No
<b>Step 1</b> <b>a</b> Clean the scanner glass and the ADF glass with a damp, soft, lint-free cloth. <b>b</b> Make sure that the document or photo is loaded facedown on the upper left corner of the scanner glass. <b>c</b> Copy the document or photo.  Is the copy quality satisfactory?	The problem is solved.	Go to step 2.
<b>Step 2</b> <b>a</b> Check the quality of the original document or photo. <b>b</b> Adjust the scan quality settings. <b>c</b> Copy the document or photo.  Is the copy quality satisfactory?	The problem is solved.	Contact <a href="#">customer support</a> .

## Scan job was not successful

Action	Yes	No
<b>Step 1</b> Check the cable connections. <b>a</b> Make sure that the Ethernet or USB cable is securely connected to the computer and the printer. <b>b</b> Resend the scan job.  Is the scan job successful?	The problem is solved.	Go to step 2.

Action	Yes	No
<b>Step 2</b> Check the file you want to scan. <b>a</b> Make sure that the file name is not already used in the destination folder. <b>b</b> Make sure that the document or photo you want to scan is not open in another application. <b>c</b> Resend the scan job.  Is the scan job successful?	The problem is solved.	Go to step 3.
<b>Step 3</b> <b>a</b> Make sure that the <b>Append time stamp</b> or the <b>Overwrite existing file</b> check box is selected in the destination configuration settings. <b>b</b> Resend the scan job.  Is the scan job successful?	The problem is solved.	Contact <a href="#">customer support</a> .

## Scanner does not close


Action	Yes	No
Remove obstructions that keep the scanner unit open.  Did the scanner unit close correctly?	The problem is solved.	Contact <a href="#">customer support</a> .

## Scanning takes too long or freezes the computer

Action	Yes	No
Close all applications that are interfering with the scan.  Does scanning take too long or freeze the computer?	Contact <a href="#">customer support</a> .	The problem is solved.

## Scanner does not respond

Action	Yes	No
<b>Step 1</b> <b>a</b> Check if the printer is turned on. <b>b</b> Resolve any error messages that appear on the display. <b>c</b> Copy or scan the document.  Is the scanner responding?	The problem is solved.	Go to step 2.

Action	Yes	No
<b>Step 2</b> <b>a</b> Check if the power cord is connected properly to the printer and the electrical outlet.  <b>CAUTION—POTENTIAL INJURY:</b> To avoid the risk of fire or electrical shock, connect the power cord to an appropriately rated and properly grounded electrical outlet that is near the product and easily accessible. <b>b</b> Copy or scan the document.  Is the scanner responding?	The problem is solved.	Go to step 3.
<b>Step 3</b> <b>a</b> Turn off the printer, wait for about 10 seconds, and then turn it back on. <b>b</b> Copy or scan the document.  Is the scanner responding?	The problem is solved.	Contact <a href="#">customer support</a> .

## Contacting customer support

Before contacting customer support, make sure to have the following information:

- Printer problem
- Error message
- Printer model type and serial number

Go to <http://support.lexmark.com> to receive e-mail or chat support, or browse through the library of manuals, support documentation, drivers, and other downloads.

Technical support via telephone is also available. In the U.S. or Canada, call 1-800-539-6275. For other countries or regions, go to <http://support.lexmark.com>.

# Upgrading and migrating

## Hardware

### Available internal options


- Memory card
  - DDR3 DIMM
  - Flash memory
    - Fonts
  - Application cards
    - Forms and Bar Code
    - PRESCRIBE
    - IPDS
- Lexmark Internal Solutions Port (ISP)
  - MarkNet™ N8360 (802.11 b/g/n/a wireless print server bundled with LEX-M06-001 Mobile Solutions Module)
  - IEEE 1284-B Parallel Card
  - RS-232C Serial Card

### Installing a memory card

**⚠ CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, if you are accessing the controller board or installing optional hardware or memory devices sometime after setting up the printer, then turn the printer off, and unplug the power cord from the electrical outlet before continuing. If you have any other devices attached to the printer, then turn them off as well, and unplug any cables going into the printer.

- 1 Turn off the printer, and then unplug the power cord from the electrical outlet.
- 2 Using a flat-head screwdriver, remove the controller board access cover.


**Warning—Potential Damage:** Controller board electronic components are easily damaged by static electricity. Touch a metal surface on the printer before touching any controller board components or connectors.




- 3 Unpack the memory card.

**Warning—Potential Damage:** Avoid touching the connection points along the edge of the card.

- 4 Insert the memory card until it *clicks* into place.



- 5 Reattach the access cover.



- 6 Connect the power cord to the electrical outlet, and then turn on the printer.


**CAUTION—POTENTIAL INJURY:** To avoid the risk of fire or electrical shock, connect the power cord to an appropriately rated and properly grounded electrical outlet that is near the product and easily accessible.

## Installing an internal solutions port


**CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, if you are accessing the controller board or installing optional hardware or memory devices sometime after setting up the printer, then turn the printer off, and unplug the power cord from the electrical outlet before continuing. If you have any other devices attached to the printer, then turn them off as well, and unplug any cables going into the printer.

- 1 Turn off the printer, and then unplug the power cord from the electrical outlet.
- 2 Using a flat-head screwdriver, remove the controller board access cover.

**Warning—Potential Damage:** Controller board electronic components are easily damaged by static electricity. Touch a metal surface on the printer before touching any controller board components or connectors.



**3** Unpack the internal solutions port (ISP) kit.




<b>1</b>	ISP
<b>2</b>	Mounting bracket
<b>3</b>	Thumbscrews


**4** If necessary, remove the printer hard disk.



**5** Insert the bracket into the board until it *clicks* into place.




**6** Attach the ISP to the bracket.




**7** If necessary, attach the hard disk to the ISP.

**a** Remove the hard disk bracket.




**b** Connect the hard disk to the ISP.

**Warning—Potential Damage:** Do not touch or press the center of the hard disk.



- 8 Reattach the access cover.



- 9 Connect the power cord to the electrical outlet, and then turn on the printer.


**CAUTION—POTENTIAL INJURY:** To avoid the risk of fire or electrical shock, connect the power cord to an appropriately rated and properly grounded electrical outlet that is near the product and easily accessible.

## Installing an optional card

**CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, if you are accessing the controller board or installing optional hardware or memory devices sometime after setting up the printer, then turn the printer off, and unplug the power cord from the electrical outlet before continuing. If you have any other devices attached to the printer, then turn them off as well, and unplug any cables going into the printer.

- 1 Turn off the printer, and then unplug the power cord from the electrical outlet.
- 2 Using a flat-head screwdriver, remove the controller board access cover.


**Warning—Potential Damage:** Controller board electronic components are easily damaged by static electricity. Touch a metal surface on the printer before touching any components or connectors.



- 3 Unpack the optional card.

**Warning—Potential Damage:** Avoid touching the connection points along the edge of the card.


- 4 Push the card firmly into place.



**Note:** The entire length of the connector on the card must touch and be flush against the controller board.

**Warning—Potential Damage:** Improper installation of the card may cause damage to the card and the controller board.

- 5 Reattach the access cover.



- 6 Connect the power cord to the electrical outlet, and then turn on the printer.


**CAUTION—POTENTIAL INJURY:** To avoid the risk of fire or electrical shock, connect the power cord to an appropriately rated and properly grounded electrical outlet that is near the product and easily accessible.

## Installing a printer hard disk

**CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, if you are accessing the controller board or installing optional hardware or memory devices sometime after setting up the printer, then turn the printer off, and unplug the power cord from the electrical outlet before continuing. If you have any other devices attached to the printer, then turn them off as well, and unplug any cables going into the printer.

- 1 Turn off the printer, and then unplug the power cord from the electrical outlet.
- 2 Using a flat-head screwdriver, remove the controller board access cover.



**Warning—Potential Damage:** Controller board electronic components are easily damaged by static electricity. Touch a metal surface on the printer before touching any controller board components or connectors.



**3** Unpack the hard disk.


**4** Attach the hard disk to the controller board.

**Warning—Potential Damage:** Do not touch or press the center of the hard disk.




If an internal solutions port (ISP) is installed, then do the following:


- a** Remove the hard disk bracket.



- b** Attach the hard disk to the ISP.



**5** Reattach the access cover.



**6** Connect the power cord to the electrical outlet, and then turn on the printer.

**CAUTION—POTENTIAL INJURY:** To avoid the risk of fire or electrical shock, connect the power cord to an appropriately rated and properly grounded electrical outlet that is near the product and easily accessible.


## Installing optional trays

**CAUTION—SHOCK HAZARD:** To avoid the risk of electrical shock, if you are accessing the controller board or installing optional hardware or memory devices sometime after setting up the printer, then turn the printer off, and unplug the power cord from the electrical outlet before continuing. If you have any other devices attached to the printer, then turn them off as well, and unplug any cables going into the printer.

**CAUTION—TIPPING HAZARD:** Installing one or more options on your printer or MFP may require a caster base, furniture, or other feature to prevent instability causing possible injury. For more information on supported configurations, see [www.lexmark.com/multifunctionprinters](http://www.lexmark.com/multifunctionprinters).


- 1** Turn off the printer.
- 2** Unplug the power cord from the electrical outlet, and then from the printer.
- 3** Unpack the optional tray, and then remove all packing material.
- 4** Lift the printer using the side and rear handles.

**CAUTION—POTENTIAL INJURY:** If the printer weight is greater than 18 kg (40 lb), then it requires two or more trained personnel to lift it safely.



**Note:** If optional trays are already installed, then unlock them from the printer before lifting the printer. Do not try to lift the printer and trays at the same time.

- 5 Align the printer with the optional tray, and then lower the printer until it *clicks* into place.



- 6 Connect the power cord to the printer, and then to the electrical outlet.



**CAUTION—POTENTIAL INJURY:** To avoid the risk of fire or electrical shock, connect the power cord to an appropriately rated and properly grounded electrical outlet that is near the product and easily accessible.

- 7 Turn on the printer.

If necessary, manually add the tray in the print driver to make it available for print jobs. For more information, see [“Adding available options in the print driver” on page 200](#).

When installing more than one hardware option, follow this order of installation.


- Caster base
- Optional 2200-sheet tray
- Optional 550-sheet tray or envelope tray




- Printer
- Staple finisher

## Installing the keyboard tray

- 1 Turn off the printer.
- 2 Open door A.




- 3 Remove the keyboard attach cover.




- 4 Unpack the keyboard tray.

**5** Attach the keyboard to the base.



**6** Insert the keyboard tray.




**7** Close door A.


**8** Turn on the printer.

## Installing the staple finisher


- 1 Turn off the printer.
- 2 Open door C.



- 3 Remove the paper bail.




- 4 Remove the paper transport and staple finisher connector covers.



- 5 Unpack the staple finisher.

- 6 Insert the staple finisher until it *clicks* into place.



- 7 Close door C.



**CAUTION—PINCH HAZARD:** To avoid the risk of a pinch injury, keep hands clear of the labeled area when closing door C.

- 8 Turn on the printer.

## Installing the multiposition staple, hole punch finisher




**CAUTION—TIPPING HAZARD:** Installing one or more options on your printer or MFP may require a caster base, furniture, or other feature to prevent instability causing possible injury. For more information on supported configurations, see [www.lexmark.com/multifunctionprinters](http://www.lexmark.com/multifunctionprinters).


- 1 From the control panel, press and hold the power button for 5 seconds to turn off the printer.
- 2 Unplug the power cord from the electrical outlet, and then from the printer.
- 3 Lock the caster base wheels to keep the printer from moving.





- 4** Open the covers at the right side of the caster base.




- 5** Open door C.




**6** Remove the wire paper bail.**7** Remove the covers.**8** Unpack the paper transport, and then remove the pieces of tape.

9 Lift, and then align the paper transport to the printer.



10 Firmly push the paper transport until it *clicks* into place.




11 Close door C.



**CAUTION—PINCH HAZARD:** To avoid the risk of a pinch injury, keep hands clear of the labeled area when closing door C.





**12** Unpack the multiposition staple, hole punch finisher, and then remove the pieces of tape.

**13** On a flat, sturdy, and stable surface, align the finisher to the printer.

**Note:** Avoid installing the finisher on a carpeted surface.



- 14** Push the finisher to the printer, and then apply pressure with your foot at the bottom of the finisher until it *clicks* into place.



- 15** Give the finisher a hard pull to check if it detaches from the printer. If the finisher detaches, then repeat [step 13](#) and [step 14](#) until they are properly locked.




**16** When the finisher is locked, do the following:

- a** Open the bottom front door of the finisher.




- b** Turn the levers of the finisher counterclockwise until the levers are loose.





- c** Close the door.

**17** Check the gap between the printer and the finisher. If the gap is uneven, then rotate the side wheels of the finisher clockwise.




- 18 Connect the power cords to the finisher and the printer, and then connect them to the electrical outlet.

 **CAUTION—POTENTIAL INJURY:** To avoid the risk of fire or electrical shock, connect the power cord to an appropriately rated and properly grounded electrical outlet that is near the product and easily accessible.

 **CAUTION—POTENTIAL INJURY:** Do not use this product with extension cords, multioutlet power strips, multioutlet extenders, or UPS devices. The power capacity of these types of accessories can be easily overloaded by a laser printer and may result in a risk of fire, property damage, or poor printer performance.

- 19 Turn on the printer.

If necessary, manually add the finisher in the print driver to make it available for print jobs.

 **CAUTION—PINCH HAZARD:** To avoid the risk of a pinch injury, keep hands clear of the labeled area during print jobs that use the stapler in the multiposition staple, hole punch finisher.

## Software

### Installing the printer software

- 1 Obtain a copy of the software installer package.
  - From the software CD that came with your printer.
  - Go to <http://support.lexmark.com>, and then select your printer and operating system.

- 2 Run the installer, and then follow the instructions on the computer screen.

- 3 For Macintosh users, add the printer.

**Note:** Obtain the printer IP address from the TCP/IP section in the Network/Ports menu.

### Adding available options in the print driver

#### For Windows users

- 1 Open the printers folder.
- 2 Select the printer you want to update, and then do either of the following:
  - For Windows 7 or later, select **Printer properties**.
  - For earlier versions, select **Properties**.
- 3 Navigate to the Configuration tab, and then select **Update Now - Ask Printer**.
- 4 Apply the changes.

#### For Macintosh users

- 1 From System Preferences in the Apple menu, navigate to your printer, and then select **Options & Supplies**.
- 2 Navigate to the list of hardware options, and then add any installed options.
- 3 Apply the changes.

# Firmware

## Exporting or importing a configuration file

You can export the configuration settings of your printer into a text file, and then import the file to apply the settings to other printers.

- 1 Open a web browser, and then type the printer IP address in the address field.

**Notes:**

- View the printer IP address on the printer home screen. The IP address appears as four sets of numbers separated by periods, such as 123.123.123.123.
- If you are using a proxy server, then temporarily disable it to load the web page correctly.

- 2 Export or import a configuration file for one or multiple applications.

**For one application**

- a From the Embedded Web Server, click **Apps** > the application that you want > **Configure**.
- b Click **Export** or **Import**.

**For multiple applications**

- a From the Embedded Web Server, click **Export Configuration** or **Import Configuration**.
- b Follow the instructions on the screen.

## Updating firmware

Some applications require a minimum device firmware level to operate correctly.

For more information on updating the device firmware, contact your Lexmark representative.

- 1 From the Embedded Web Server, click **Settings** > **Device** > **Update Firmware**.
- 2 Browse to locate the required flash file.
- 3 Apply the changes.

# Notices

## Product information

Product name:

Lexmark XC8155de, XC8155dte, XC8160de, XC8160dte

Machine type:

7564

Model(s):

596, 598

## Edition notice

February 2018

**The following paragraph does not apply to any country where such provisions are inconsistent with local law:** LEXMARK INTERNATIONAL, INC., PROVIDES THIS PUBLICATION "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some states do not allow disclaimer of express or implied warranties in certain transactions; therefore, this statement may not apply to you.

This publication could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in later editions. Improvements or changes in the products or the programs described may be made at any time.

References in this publication to products, programs, or services do not imply that the manufacturer intends to make these available in all countries in which it operates. Any reference to a product, program, or service is not intended to state or imply that only that product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any existing intellectual property right may be used instead. Evaluation and verification of operation in conjunction with other products, programs, or services, except those expressly designated by the manufacturer, are the user's responsibility.

For Lexmark technical support, visit <http://support.lexmark.com>.

For information on supplies and downloads, visit [www.lexmark.com](http://www.lexmark.com).

© 2016 Lexmark International, Inc.

All rights reserved.

## GOVERNMENT END USERS

The Software Program and any related documentation are "Commercial Items," as that term is defined in 48 C.F.R. 2.101, "Computer Software" and "Commercial Computer Software Documentation," as such terms are used in 48 C.F.R. 12.212 or 48 C.F.R. 227.7202, as applicable. Consistent with 48 C.F.R. 12.212 or 48 C.F.R. 227.7202-1 through 227.7202-4, as applicable, the Commercial Computer Software and Commercial Software Documentation are licensed to the U.S. Government end users (a) only as Commercial Items and (b) with only those rights as are granted to all other end users pursuant to the terms and conditions herein.

## Licensing notices

All licensing notices associated with this product can be viewed from the CD:\NOTICES directory of the installation software CD.

## Trademarks

Lexmark, the Lexmark logo, and MarkNet are trademarks or registered trademarks of Lexmark International, Inc. in the United States and/or other countries.

Google Cloud Print and Google Chrome are trademarks of Google Inc.

Macintosh, the Mac logo, and Safari are trademarks of Apple Inc.

Microsoft, Windows, and Internet Explorer are either registered trademarks or trademarks of the Microsoft group of companies in the United States and other countries.

Mopria®, the Mopria® logo, and the Mopria® Alliance logo are registered trademarks and service marks of Mopria Alliance, Inc. in the United States and other countries. Unauthorized use is strictly prohibited.

PCL® is a registered trademark of the Hewlett-Packard Company. PCL is Hewlett-Packard Company's designation of a set of printer commands (language) and functions included in its printer products. This printer is intended to be compatible with the PCL language. This means the printer recognizes PCL commands used in various application programs, and that the printer emulates the functions corresponding to the commands.

PostScript is a registered trademark of Adobe Systems Incorporated in the United States and/or other countries.

All other trademarks are the property of their respective owners.

AirPrint and the AirPrint logo are trademarks of Apple, Inc.

## Noise emission levels


The following measurements were made in accordance with ISO 7779 and reported in conformance with ISO 9296.

**Note:** Some modes may not apply to your product.

1-meter average sound pressure, dBA	
Printing	One-sided: 55 (mono), 56 (color); Two-sided: 57 (mono), 57 (color)
Scanning	56 (XC8155); 55 (XC8160)
Copying	58 (mono); 59 (color)
Ready	16 (XC8155); 14 (XC8160)

Values are subject to change. See [www.lexmark.com](http://www.lexmark.com) for current values.

## Static sensitivity notice



This symbol identifies static-sensitive parts. Do not touch the areas near these symbols without first touching a metal surface in an area away from the symbol.

## Temperature information

Operating temperature and relative humidity	10 to 32.2°C (50 to 90°F) and 15 to 80% RH 15.3 to 32.2°C (60 to 90°F) and 8 to 15% RH Maximum wet bulb temperature: 22.8°C (73°F)
Shipping temperature	-40 to 43.3°C (-40 to 110°F)
Storage temperature and relative humidity	-40 to 43.3°C (-40 to 110°F) 8 to 80% RH

## Laser notice

The printer is certified in the U.S. to conform to the requirements of DHHS 21 CFR, Chapter I, Subchapter J for Class I (1) laser products, and elsewhere is certified as a Class I laser product conforming to the requirements of IEC 60825-1: 2014.

Class I laser products are not considered to be hazardous. The printer contains internally a Class IIIb (3b) AlGaAs laser that is nominally 20 milliwatts operating in the wavelength region of 755–800 nanometers and enclosed in a non-serviceable printhead assembly. The laser system and printer are designed so there is never any human access to laser radiation above a Class I level during normal operation, user maintenance, or prescribed service conditions.

## Laser advisory label

A laser notice label may be affixed to this printer as shown:

DANGER - Invisible laser radiation when cartridges are removed and interlock defeated. Avoid exposure to laser beam.

PERIGO - Radiação a laser invisível será liberada se os cartuchos forem removidos e o lacre rompido. Evite a exposição aos feixes de laser.

Opasnost - Nevidljivo lasersko zračenje kada su kasete uklonjene i poništena sigurnosna veza. Izbjegavati izlaganje zracima.

NEBEZPEČÍ - Když jsou vyjmuty kazety a je odblokována pojistka, ze zařízení je vysíláno neviditelné laserové záření. Nevystavujte se působení laserového paprsku.

FARE - Usynlig laserstråling, når patroner fjernes, og spærreanordningen er slået fra. Undgå at blive udsat for laserstrålen.



GEVAAR - Onzichtbare laserstraling wanneer cartridges worden verwijderd en een vergrendeling wordt genegeerd. Voorkom blootstelling aan de laser.

DANGER - Rayonnements laser invisibles lors du retrait des cartouches et du déverrouillage des loquets. Eviter toute exposition au rayon laser.

VAARA - Näkymätöntä lasersäteilyä on varottava, kun värikasetit on poistettu ja lukitus on auki. Vältä lasersäteelle altistumista.

GEFAHR - Unsichtbare Laserstrahlung beim Herausnehmen von Druckkassetten und offener Sicherheitssperre. Laserstrahl meiden.

KINΔΥΝΟΣ - Έκλυση αόρατης ακτινοβολίας laser κατά την αφαίρεση των κασετών και την απασφάλιση της μανδάλωσης. Αποφεύγετε την έκθεση στην ακτινοβολία laser.

VESZÉLY – Nem látható lézersugárzás fordulhat elő a patronok eltávolításakor és a zárószerkezet felbontásakor. Kerülje a lézersugárnak való kitettséget.

PERICOLO - Emissione di radiazioni laser invisibili durante la rimozione delle cartucce e del blocco. Evitare l'esposizione al raggio laser.

FARE – Usynlig laserstråling når kassetten tas ut og sperren er satt ut av spill. Unngå eksponering for laserstrålen.

NIEBEZPIECZEŃSTWO - niewidzialne promieniowanie laserowe podczas usuwania kaset i blokady. Należy unikać naświetlenia promieniem lasera.

ОПАСНО! Невидимое лазерное излучение при извлеченных картриджах и снятии блокировки. Избегайте воздействия лазерных лучей.

Pozor – Nebezpečenstvo neviditeľného laserového žiarenia pri odobratých kazetách a odblokovanej poistke. Nevystavujte sa lúčom.

PELIGRO: Se producen radiaciones láser invisibles al extraer los cartuchos con el interbloqueo desactivado. Evite la exposición al haz de láser.

FARA – Osynlig laserstrålning när patroner tas ur och spärrmekanismen är upphävd. Undvik exponering för laserstrålen.

危険 - 当移除碳粉盒及互锁失效时会产生看不见的激光辐射，请避免暴露在激光光束下。

危険 - 移除碳粉匣與安全連鎖開關失效時會產生看不見的雷射輻射。請避免曝露在雷射光束下。

危険 - カートリッジが取り外され、内部ロックが無効になると、見えないレーザー光が放射されます。このレーザー光に当たらないようにしてください。

# Index

## A

- activating Voice Guidance 27
- adapter plug 51
- adding contacts 24
- adding groups 25
- adding hardware options
  - print driver 200
- adding internal options
  - print driver 200
- ADF feed roller
  - replacing 96
- ADF pick roller
  - replacing 94
- ADF separator roller
  - replacing 98
- adjusting speech rate
  - Voice Guidance 27
- adjusting the brightness
  - printer display 109
- adjusting the brightness of the printer display 109
- adjusting the default headphones volume 63
- adjusting the default speaker volume 63
- adjusting toner darkness 168
- AirPrint
  - using 34
- answering machine
  - setting up 43
- attaching cables 14
- available internal options 178
- avoiding paper jams 111

## B

- blank pages 149
- blocking junk faxes 57

## C

- canceling a print job
  - from the computer 37
  - from the printer control panel 37
- cannot open Embedded Web Server 136
- Card Copy
  - setting up 21

- card stock
  - loading 31
- changing port settings
  - internal solutions port 64
- Check tray connection 144
- checking the printer connectivity 137
- checking the status of parts and supplies 68
- cleaning
  - exterior of the printer 65
  - interior of the printer 65
  - scanner glass 66
- cleaning the printer 65
- collated printing does not work 142
- collating copies 39
- Color Correction
  - manual 168
- Color Correction Content 168
- color quality, troubleshooting
  - print appears tinted 170
- confidential print jobs 36
- configuring
  - fax speaker settings 63
- configuring daylight saving time 55
- configuring e-mail settings 40
- configuring port settings 64
- configuring supply notifications 70
- connecting printer to distinctive ring service 55
- connecting to a wireless network
  - using PIN method 64
  - using Push Button method 64
- conservation settings
  - Eco-Mode 108
  - hibernate mode 108
  - sleep mode 108
- conserving supplies 109
- contacting customer support 177
- contacts
  - adding 24
  - deleting 25
  - editing 25
- control panel
  - using 16

- copy troubleshooting
  - partial copies of documents or photos 175
  - poor copy quality 175
  - scanner does not respond 176
  - scanner unit does not close 176
- copying
  - creating shortcuts 39
  - on both sides of the paper 38
- copying different paper sizes 38
- copying from
  - selected tray 38
- copying multiple pages
  - onto a single sheet 39
- copying on letterhead 38
- copying photos 38
- creating shortcuts
  - e-mail 41
  - fax destination 56
- Customer Support
  - using 22
- customer support
  - contacting 177
- customizing the display 24

## D

- date and time
  - fax settings 55
- daylight saving time, configuring 55
- default headphones volume
  - adjusting 63
- default speaker volume
  - adjusting 63
- Defective flash detected 140
- deleting contacts 25
- deleting groups 25
- developer unit
  - ordering 69
  - replacing 71
- Device Quotas
  - setting up 22
- different paper sizes, copying 38
- digital subscriber line (DSL)
  - fax setup 47
- digital telephone service
  - fax setup 49

- directory list
  - printing 37
- disabling the proximity sensor 109
- Display Customization
  - using 24
- disposing of printer hard disk 61
- distinctive ring service, fax
  - connecting to 55
- documents, printing
  - from a computer 33
  - from a mobile device 33, 34
- DSL filter 47

## E

- Eco-Mode setting 108
- Eco-Settings
  - configuring 24
- editing contacts 25
- editing groups 25
- emission notices 203
- emptying the hole punch box 67
- enabling Magnification mode 27
- enabling personal identification numbers 27
- enabling spoken passwords 27
- enabling the USB port 137
- encrypting the printer hard disk 61
- enlarging copies 39
- envelopes
  - loading 31
- environmental setting
  - Eco-Mode 108
- environmental settings
  - hibernate mode 108
  - sleep mode 108
- erasing printer hard disk memory 60
- exporting a configuration file
  - using the Embedded Web Server 201
- e-mail
  - creating shortcuts 41
  - setting up 40
- e-mailing
  - configuring e-mail settings 40
  - using a shortcut number 40
  - using the address book 40
  - using the printer 40

## F

- FAQ about color printing 169
- fax log
  - viewing 57
- fax resolution
  - changing 56
- fax setup
  - country- or region-specific 51
  - digital telephone service 49
  - DSL connection 47
  - standard telephone line connection 43
  - VoIP 48
- fax speaker settings
  - configuring 63
- fax troubleshooting
  - cannot receive faxes 173
  - cannot send faxes 173
  - cannot send or receive faxes 171
  - received fax has poor print quality 174
- faxing
  - adjusting darkness 56
  - blocking junk faxes 57
  - changing resolution 56
  - creating shortcuts 56
  - fax setup 42
  - forwarding faxes 57
  - holding faxes 57
  - setting the date and time 55
  - viewing a fax log 57
- finding more information about the printer 10
- firmware
  - update 201
- firmware card 178
- flash drive
  - printing from 34
  - scanning to 58
- font sample list
  - printing 37
- forms
  - printing 33
- Forms and Favorites
  - setting up 21
- forwarding faxes 57
- FTP address
  - creating shortcuts 58
- FTP server, scanning to
  - using the control panel 58

- fuser
  - replacing 73

## G

- Google Cloud Print
  - using 33
- green settings
  - Eco-Mode 108
  - hibernate mode 108
  - sleep mode 108
- groups
  - adding 25
  - deleting 25
  - editing 25

## H

- hardware options
  - installing 187
- hardware options, adding
  - print driver 200
- headphones
  - default volume 63
- held jobs 36
  - printing from a Macintosh computer 36
  - printing from Windows 36
- held print jobs
  - printing from a Macintosh computer 36
  - printing from Windows 36
- hibernate mode
  - setting 108
- holding faxes 57
- hole punch box
  - emptying 67
- home screen
  - customizing 21
  - showing icons 21
- home screen icons
  - using 17
- horizontal dark lines 153

## I

- icons on the home screen
  - showing 21
- imaging unit
  - replacing 78
- imaging units
  - ordering 70

- importing a configuration file
  - using the Embedded Web Server 201
- indicator light
  - printer status 17
- installing a memory card 178
- installing a printer hard disk 184
- installing an internal solutions port 179
- installing an optional card 183
- installing optional trays 187
- installing options
  - internal solutions port 179
  - printer hard disk 184
- installing the keyboard tray 189
- installing the multiposition staple, hole punch finisher 193
- installing the printer software 200
- installing the staple finisher 191
- internal options 178
  - installing 183
  - memory card 178
- internal options, adding
  - print driver 200
- internal solutions port
  - installing 179
  - troubleshooting 139

## J

- jam, clearing
  - automatic document feeder 116
  - door J 129
  - door K 127
  - door L 131
  - door N 130
  - duplex unit 119
  - finisher bin 122
  - fuser 119
  - multipurpose feeder 115
  - standard bin 118
  - staple cartridge 124, 133
  - staple finisher bin 132
  - trays 114
- jams
  - avoiding 111
  - locating jam areas 112
  - locations 112

## K

- keyboard on the display
  - using 28
- keyboard tray
  - installing 189

## L

- letterhead
  - copying on 38
- Lexmark Mobile Print
  - using 33
- line filter 47
- linking trays 32
- loading
  - card stock 31
  - envelopes 29
  - transparencies 31
  - trays 29
- loading envelopes
  - multipurpose feeder 31
- loading paper
  - multipurpose feeder 31
- locating the security slot 60

## M

- Magnification mode
  - enabling 27
- making copies 38
- manual Color Correction
  - applying 168
- memory
  - types installed on printer 61
- memory card 178
  - installing 178
- menu map 18
- menu settings page
  - printing 20
- mobile device
  - printing from 33, 34
- Mopria Print Service
  - using 34
- moving the printer 11, 108
- multiposition staple, hole punch finisher
  - installing 193
- multipurpose feeder
  - loading 31

## N

- navigating the screen
  - using gestures 28
- navigating the screen using gestures 28
- noise emission levels 203
- Non-Lexmark supply 141
- non-volatile memory 61
  - erasing 60
- Not enough free space in flash memory for resources 140
- notices 203

## O

- optional card
  - installing 183
- optional trays
  - installing 187
- options
  - firmware cards 178
  - memory card 178
- ordering
  - developer unit 69
  - imaging units 70
  - photoconductor unit 69
  - toner cartridges 68
- ordering supplies
  - staple cartridges 70
  - waste toner bottle 70

## P

- paper
  - Universal size setting 29
- paper jam behind door N 130
- paper jam in door B 119
- paper jam in door J 129
- paper jam in door K 127
- paper jam in door L 131
- paper jam in the automatic document feeder 116
- paper jam in the finisher bin 122
- paper jam in the multipurpose feeder 115
- paper jam in the standard bin 118
- paper jam in the staple finisher bin 132
- paper jam in trays 114
- paper jam, clearing
  - automatic document feeder 116
  - door J 129
  - door K 127

- door L 131
- door N 130
- duplex unit 119
- finisher bin 122
- fuser 119
- multipurpose feeder 115
- standard bin 118
- staple finisher bin 132
- trays 114
- paper jams
  - avoiding 111
- paper size
  - setting 29
- paper type
  - setting 29
- parallel interface card
  - troubleshooting 139
- parts status
  - checking 68
- personal identification number
  - method 64
- personal identification numbers
  - enabling 27
- phone splitter 48
- photoconductor unit
  - ordering 69
  - replacing 75
- photos
  - copying 38
- pick roller
  - replacing 82
- placing separator sheets
  - between copies
    - copying 39
- port settings
  - configuring 64
- power button light
  - printer status 17
- print driver
  - hardware options, adding 200
- print job
  - canceling from the
    - computer 37
  - canceling from the printer
    - control panel 37
- print quality
  - cleaning the scanner glass 66
- print quality troubleshooting
  - blank pages 149
  - crooked print 159
  - dark print 150
  - ghost images appear on
    - prints 152
  - gray background 152
  - horizontal dark lines 153
  - horizontal white lines 154
  - jagged or uneven
    - characters 156
  - light print 157
  - mottled print and dots 158
  - repeating print defects 160
  - skewed print 159
  - solid color or black images 161
  - text or images cut off 162
  - toner easily rubs off 163
  - uneven print density 163
  - vertical dark lines or streaks
    - appear on prints 164
  - white lines 165
  - white pages 149
- print troubleshooting
  - confidential and other held
    - documents do not print 146
  - envelope seals when
    - printing 142
  - incorrect margins on prints 155
  - jammed pages are not
    - reprinted 145
  - job prints from the wrong
    - tray 167
  - job prints on the wrong
    - paper 167
  - paper curl 143
  - paper frequently jams 145
  - print jobs do not print 148
  - slow printing 147
  - tray linking does not work 143
  - unable to read flash drive 137
- printer
  - basic model 12
  - fully configured 12
  - minimum clearances 11
  - moving 11, 108
  - selecting a location 11
  - shipping 108
- printer configurations 12
- printer display
  - adjusting the brightness 109
- printer hard disk
  - disposing of 61
  - encrypting 61
- printer hard disk encryption 61
- printer hard disk memory
  - erasing 60
- printer information
  - finding 10
- printer is not responding 166
- printer menus 18
- printer messages
  - Check tray connection 144
  - Defective flash detected 140
  - Non-Lexmark supply 141
  - Not enough free space in flash
    - memory for resources 140
  - Replace cartridge, printer region
    - mismatch 140
  - Scanner maintenance required,
    - use ADF Kit 141
  - Unformatted flash detected 140
- printer options troubleshooting
  - internal option is not
    - detected 138
  - internal solutions port 139
  - parallel interface card 139
  - serial interface card 139
- printer ports 14
- printer settings
  - restoring to factory defaults 61
- printer software, installing 200
- printing
  - directory list 37
  - font sample list 37
  - from a computer 33
  - from a flash drive 34
  - from a mobile device 34
  - menu settings page 20
  - printing a directory list 37
  - printing a font sample list 37
  - printing a menu settings
    - page 20
  - printing a network setup
    - page 137
  - printing forms 33
  - printing from a computer 33
  - printing from a flash drive 34
  - printing from Google Drive 23
  - printing held jobs
    - from a Macintosh computer 36
    - from Windows 36
  - Push Button method 64
- Q**
  - QR codes
    - adding 23

**R**

- recycling
  - Lexmark packaging 110
  - Lexmark products 109
  - toner cartridges 110
- reducing copies 39
- repeat print jobs 36
  - printing from a Macintosh computer 36
  - printing from Windows 36
- repeating print defects 160
- Replace cartridge, printer region mismatch 140
- replacing a developer unit 71
- replacing a photoconductor unit 75
- replacing a toner cartridge 81
- replacing an imaging unit 78
- replacing parts
  - ADF feed roller 96
  - ADF pick roller 94
  - ADF separator roller 98
  - pick roller 82
  - separator bracket 87
- replacing supplies
  - staple cartridge 99, 104
  - staple cartridge holder 101, 106
  - waste toner bottle 88
- replacing the ADF feed roller 96
- replacing the ADF pick roller 94
- replacing the ADF separator roller 98
- replacing the fuser 73
- replacing the pick roller 82
- replacing the separator bracket 87
- replacing the staple cartridge holder in the multiposition staple, hole punch finisher 106
- replacing the staple cartridge holder in the staple finisher 101
- replacing the staple cartridge in the multiposition staple, hole punch finisher 104
- replacing the staple cartridge in the staple finisher 99
- replacing the transfer belt 89
- replacing the waste toner bottle 88
- replacing transfer roller 92

- reserve print jobs
  - printing from a Macintosh computer 36
  - printing from Windows 36
- resetting
  - supply usage counters 141
- resetting the supply usage counters 141
- restoring factory default settings 61
- RJ11 adapter 51

**S**

- safety information 8, 9
- saving paper 39
- saving toner 39
- Scan Center
  - setting up 22
- Scan to Computer
  - setting up 59
- scan troubleshooting
  - cannot scan from a computer 174
  - partial copies of documents or photos 175
  - poor copy quality 175
  - scan job was not successful 175
  - scanner does not respond 176
  - scanner unit does not close 176
  - scanning freezes the computer 176
  - scanning takes too long 176
- scanner glass
  - cleaning 66
- Scanner maintenance required, use ADF Kit 141
- scanning
  - to an FTP server 58
  - scanning to a computer 59
  - scanning to a flash drive 58
  - scanning to an FTP server using the control panel 58
  - scanning to Google Drive 23
- scheduling a fax 56
- security slot
  - locating 60
- selecting a location for the printer 11
- sending a fax
  - scheduled 56
  - using the computer 55
  - using the control panel 55
- sending an e-mail 40
- separator bracket
  - replacing 87
- serial interface card
  - troubleshooting 139
- serial printing
  - setting up 65
- setting hibernate mode 108
- setting sleep mode 108
- setting the paper size 29
- setting the paper type 29
- setting the Universal paper size 29
- setting up Device Quotas 22
- setting up e-mail function 40
- setting up fax
  - country- or region-specific 51
  - digital telephone service 49
  - DSL connection 47
  - standard telephone line connection 43
  - VoIP connection 48
- setting up fax function 42
- setting up serial printing 65
- shipping the printer 108
- Shortcut Center
  - using 22
- shortcuts, creating
  - copy screen 39
  - FTP address 58
- showing icons on the home screen 21
- speaker
  - default volume 63
- spoken passwords
  - enabling 27
- staple cartridge
  - replacing 99, 104
- staple cartridge holder
  - replacing 101, 106
- staple cartridges
  - ordering 70
- staple finisher
  - installing 191
- staple jam in door G 124
- staple jam in door J 133
- staple jam, clearing
  - door G 124
  - door J 133
- statement of volatility 61
- storing
  - supplies 107

- storing print jobs 36
- supplies
  - conserving 109
  - storing 107
- supplies status
  - checking 68
- supplies, ordering
  - developer unit 69
  - imaging units 70
  - photoconductor unit 69
  - staple cartridges 70
  - toner cartridges 68
  - waste toner bottle 70
- supply notifications
  - configuring 70
- supply usage counters
  - resetting 141
- supported file types 35
- supported flash drives 35

## T

- toner cartridge
  - replacing 81
- toner cartridges
  - ordering 68
  - recycling 110
- toner darkness
  - adjusting 168
- transfer belt
  - replacing 89
- transfer roller
  - replacing 92
- transparencies
  - loading 31
- trays
  - linking 32
  - loading 29
  - unlinking 32
- troubleshooting
  - cannot open Embedded Web Server 136
  - FAQ about color printing 169
  - printer is not responding 166
  - troubleshooting, color quality
    - print appears tinted 170
  - troubleshooting, copy
    - partial copies of documents or photos 175
    - poor copy quality 175
    - scanner does not respond 176
    - scanner unit does not close 176

- troubleshooting, fax
  - cannot receive faxes 173
  - cannot send faxes 173
  - cannot send or receive faxes 171
  - received fax has poor print quality 174
- troubleshooting, print
  - collated printing does not work 142
  - confidential and other held documents do not print 146
  - envelope seals when printing 142
  - incorrect margins on prints 155
  - jammed pages are not reprinted 145
  - job prints from the wrong tray 167
  - job prints on the wrong paper 167
  - paper curl 143
  - paper frequently jams 145
  - print jobs do not print 148
  - slow printing 147
  - tray linking does not work 143
- troubleshooting, print quality
  - blank pages 149
  - crooked print 159
  - dark print 150
  - ghost images appear on prints 152
  - gray background 152
  - horizontal dark lines 153
  - horizontal white lines 154
  - jagged or uneven characters 156
  - light print 157
  - mottled print and dots 158
  - repeating print defects 160
  - skewed print 159
  - solid color or black images 161
  - text or images cut off 162
  - toner easily rubs off 163
  - uneven print density 163
  - vertical dark lines or streaks appear on prints 164
  - white lines on a page 165
  - white pages 149
- troubleshooting, printer options
  - internal option is not detected 138

- internal solutions port 139
- troubleshooting, scan
  - cannot scan from a computer 174
  - partial copies of documents or photos 175
  - poor copy quality 175
  - scan job was not successful 175
  - scanner does not respond 176
  - scanner unit does not close 176
- two-sided copying 38

## U

- unable to read flash drive
  - troubleshooting, print 137
- understanding the status of the power button and indicator light 17
- uneven print density 163
- Unformatted flash detected 140
- Universal paper size
  - setting 29
- unlinking trays 32
- updating firmware
  - flash file 201
- USB port
  - enabling 137
- using
  - genuine Lexmark parts 68
  - genuine Lexmark supplies 68
  - using Customer Support 22
  - using Display Customization 24
  - using Google Drive 23
  - using QR Code Generator 23
  - using the ADF
    - copying 38
  - using the control panel 16
  - using the home screen 17
  - using the keyboard on the display 28
  - using the scanner glass
    - copying 38

## V

- verify print jobs 36
  - printing from a Macintosh computer 36
  - printing from Windows 36
- vertical dark lines or streaks appear on prints 164
- vertical white lines appear 165

- viewing a fax log 57
- Voice Guidance
  - activating 27
  - speech rate 27
- Voice Guidance speech rate
  - adjusting 27
- voice mail
  - setting up 43
- voice over Internet Protocol (VoIP)
  - fax setup 48
- VoIP adapter 48
- volatile memory 61
  - erasing 60
- volatility
  - statement of 61

## W

- waste toner bottle
  - ordering 70
  - replacing 88
- white lines appear 165
- white pages 149
- wireless network
  - Wi-Fi Protected Setup 64
- Wi-Fi Protected Setup
  - wireless network 64