

Resetting the maintenance counter

Printing

Paper handling

Maintenance

Troubleshooting

Administration

Index

After replacing all the items in the **maintenance kit**, reset the maintenance counter:

- 1 Press and hold the **Select** and **Return** buttons while you turn the printer on.
- 2 Release the buttons when **Performing Self Test** appears on the display.

The printer performs its power-on sequence, and then Config Menu appears on the first line of the display.

- 3 Press **Menu** until you see Reset Maint Cnt and then press **Select**.

Reset appears on the second line of the display.

- 4 Press **Select**.

Resetting Maint Cnt Value appears briefly on the display, and then is replaced by Config Menu on the top line and Reset Maint Cnt on the second line.

- 5 Press **Menu** until you see **Exit Config Menu**, and then press **Select**.

Activating Menu Changes appears briefly, followed by **Performing Self Test**. The printer returns to the Ready state.

