

How to Set-up Non-IPDS Printing using Host Print Transform (HPT)

Step 1: Create non-IPDS DEVD

In the command line, type:

CRTDEVPRT *[press enter]*

Then fill up the following fields:

Device description: MS810HPT *[or you can have any name]*

Device class: *LAN

Device type: 3812

Device Model: 1

Lan attachment: *IP

Port number: 9100

Online at IPL: *YES

Font:

Identifier: 11

Point size: *NONE

Form feed: *AUTOCUT

Separator drawer: *FILE

Separator program: *NONE

Library:

Press Enter.

Activation timer: 170

Inactivity Timer: *SEC15

Host print transform: *YES

Press Enter.

Manufacturer type and model: *LEXMARKT634 *[or press F4 and choose the closest model]*

Paper source 1: *MFRTYPMDL

Paper source 2: *MFRTYPMDL

Envelope source: *MFRTYPMDL

ASCII code page 899 support: *NO

Image configuration: *NONE

Character Identifier:

Graphic character set: *SYSVAL

Code page

Remote location Name or address: 10.194.15.69 *[IP address of the printer]*

.

.

.

System driver program: *IBMPJLDRV

.

.

Workstation customizing object: none

Library

```

Create Device Desc (Printer) (CRTDEVPRT)

Type choices, press Enter.

Device description . . . . . > MS810HPT      Name
Device class . . . . . > *LAN              *LCL, *RMT, *VRT, *SNPT, *LAN
Device type . . . . . > 3812             3287, 3812, 4019, 4201...
Device model . . . . . > 1                0, 1, 2, 3, 4, 10, 13, 200...
LAN attachment . . . . . > *IP          *LEXLINK, *IP, *USRDFN
Port number . . . . . > 9100            0-65535
Online at IPL . . . . . > *YES          *YES, *NO
Font:
  Identifier . . . . . > 11             3, 5, 11, 12, 13, 18, 19...
  Point size . . . . . > *NONE          000.1-999.9, *NONE
Form feed . . . . . > *AUTOCUT        *TYPE, *CONT, *CONT2, *CUT...
Separator drawer . . . . . > *FILE          1-255, *FILE
Separator program . . . . . > *NONE          Name, *NONE
Library . . . . . > *NONE          Name, *LIBL, *CURLIB
Printer error message . . . . . > *INQ          *INQ, *INFO

More...
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys

```

```

Create Device Desc (Printer) (CRTDEVPRT)

Type choices, press Enter.

Message queue . . . . . > *CTLD          Name, QSYSOPR
Library . . . . . > *NONE          Name, *LIBL, *CURLIB
Activation timer . . . . . > 170           1-2550, *NOMAX
Inactivity timer . . . . . > *SEC15        1-30, *ATTACH, *NOMAX...
Host print transform . . . . . > *YES          *NO, *YES
Manufacturer type and model . . . > *LEXMARKT634
Paper source 1 . . . . . > *MFRTPMDL     *MFRTPMDL, *LETTER...
Paper source 2 . . . . . > *MFRTPMDL     *MFRTPMDL, *LETTER...
Envelope source . . . . . > *MFRTPMDL     *MFRTPMDL, *MONARCH...
ASCII code page 899 support . . . > *NO           *NO, *YES
Image configuration . . . . . > *NONE          *NONE, *IMGA01, *IMGA02...
Character identifier:
  Graphic character set . . . . . > *SYSVAL       1-32767
  Code page . . . . . > *NONE          1-32767

More...
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys

```

```

Create Device Desc (Printer) (CRTDEVPRT)

Type choices, press Enter.

Remote location:
  Name or address . . . . . > 10.194.15.175'

User-defined options . . . . . > *NONE          Character value, *NONE
+ for more values

User-defined object:
  Object . . . . . > *NONE          Name, *NONE
  Library . . . . . > *NONE          Name, *LIBL, *CURLIB
  Object type . . . . . > *NONE          *DTAARA, *DTAQ, *FILE...
Data transform program . . . . . > *NONE          Name, *NONE
Library . . . . . > *NONE          Name, *LIBL, *CURLIB
System driver program . . . . . > *IBMPJLDRV
Secure connection . . . . . > *NO           *NO, *YES

More...
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys

```

```

Create Device Desc (Printer) (CRTDEVPRT)

Type choices, press Enter.

Validation list . . . . . *NONE          Name, *NONE
Library . . . . .          Name, *LIBL, *CURLIB
Publishing information:
Support duplex . . . . . *UNKNOWN      *UNKNOWN, *SIMPLEX, *DUPLEX
Support color . . . . . *UNKNOWN      *UNKNOWN, *NOCOLOR, *COLOR
Pages per minute black . . . . . *UNKNOWN  1-32767, *UNKNOWN
Pages per minute color . . . . . *UNKNOWN  1-32767, *UNKNOWN
Location . . . . . *BLANK
Data streams supported . . . . . *UNKNOWN  *UNKNOWN, *PCL, *PS, *PDF...
+ for more values
Text 'description' . . . . . DEVD for HPT Printing

Additional Parameters

Remote network identifier . . . *NETATR      Name, *NETATR, *NONE
More...
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys

```

```

Create Device Desc (Printer) (CRTDEVPRT)

Type choices, press Enter.

Workstation customizing object  *NONE          Name, *NONE
Library . . . . .          Name, *LIBL, *CURLIB
Authority . . . . . *CHANGE      Name, *CHANGE, *ALL, *USE...

Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys

```

After filling up the values above, press enter to save and create the DEVD.

Step 2: Now you are ready to print!

Vary on DEVD, and turn on the MS810HPT WTR. To print the job you can either transfer the job to the MS810HPT OUTQ that was created with the DEVD or change the WTR so it points to the OUTQ containing the job you want to print.

```

Change Writer (CHGWTR)

Type choices, press Enter.

Writer . . . . . > MS810HPT      Name, *SYSVAL
Output queue . . . . . PRT01N     Name, *SAME, *DEV
Library . . . . . QGPL           Name, *LIBL, *CURLIB
Form type options:
Form type . . . . . *SAME        Form type, *SAME, *ALL...
Message option . . . . . *SAME    *SAME, *INQMSG, *MSG...
File separators . . . . . *SAME    0-9, *SAME, *FILE
Drawer for separators . . . . . *SAME 1-255, *SAME, *DEVD, *FILE
When to change writer . . . . . *NORDYF *NORDYF, *FILEEND

Bottom
F3=Exit  F4=Prompt  F5=Refresh  F12=Cancel  F13=How to use this display
F24=More keys

```