

# Print defects guide

## Identifying supplies or parts for replacement

Match a set of repeating defects on a printed page to the marks on one of the vertical lines. The line that best matches the defects on the page indicates which particular part is causing the defect.

### Notes:

- There are four additional color pages and a blank page that prints with this guide. Use these pages for assistance in determining which part is defective.
- The imaging kit is a customer replaceable part. If the transfer module or fuser needs replacement, then contact customer support at <http://support.lexmark.com> or your Lexmark service representative.

### Replace the imaging kit

### Replace the developer unit






25.1 mm  
(0.99 in.)

29.8 mm  
(1.17 in.)

94.2 mm  
(3.70 in.)


43.9 mm  
(1.72 in.)

45.5 mm  
(1.79 in.)



**Replace the transfer module**

37.7 mm  
(1.48 in.)



55.0 mm  
(2.17 in.)



78.5 mm  
(3.09 in.)



**Replace the fuser**

95 mm  
(3.74 in.)



